



FEATURING



SOFTPATCH



CUE STACK WITH GO BUTTON

Leprecon®
Pro Lighting Equipment

LP-600

CONTROLLERS

*The compact and economical 600 Series
Memory Consoles are fully featured
and designed to withstand the
most demanding conditions.*



TWO SCENE PRESET MODE

SOFTPATCH

CHASE MEMORY

BUMP BUTTONS WITH ADD AND SOLO MODES

CUE STACK AND "GO BUTTON"



Leprecon's twelve channel LP-612 or twenty-four channel LP-624 consoles incorporate the same full travel faders and rugged aluminum chassis design that make our touring consoles the most reliable in the industry. With full size fader knobs, quick action bump buttons, and big bright LED's, these consoles were designed and built for professional use.

The console includes: two scene preset mode with twelve or twenty-four channels; switchable Add or Solo momentary buttons for each channel; and dipless crossfade between manual scenes. Presets may be "piled on" in any combination, and are assigned to one of four memory pages. Preview mode allows cues to be checked without bringing up the scene on stage. An existing cue may be easily edited using the manual scene faders without re-recording the entire cue.

Cue Stack offers 50 programmable cues with crossfader and "GO" button control. Fade times may be assigned to each scene. A two character display is used to indicate current or next cue and programmed fade times assigned to each scene. Four programmed and seven programmable patterns of up to 20 steps are provided. Programmable patterns are recorded, previewed and edited as easily as the preset cues. The rate of each pattern may be saved with the chase, eliminating the need to adjust the rate pot when the chase is recalled. Control output via 3 pin microplex output allows you to hook up your lighting system using standard microphone cable. DMX-512 and Analog outputs are available. All output protocols can be used simultaneously.

For information on our compatible tree mount dimmers, call or write CAE and ask for publication #28-0036.



The 600 Series Memory Consoles

	612-MPX	612-MPX-D/A	624-MPX	624-MPX-D/A
Channel	12	12	24	24
Two Scene-Preset	●	●	●	●
Softpatch	●	●	●	●
Preset Faders	12	12	24	24
Preset Memories	48	48	96	96
Cue Stack	●	●	●	●
Go Button	●	●	●	●
Bump Buttons	●	●	●	●
Dipless Crossfader	●	●	●	●
Chase Memory	11 Patterns-24 Steps Real Level Memories	11 Patterns-24 Steps Real Level Memories	11 Patterns-24 Steps Real Level Memories	11 Patterns-24 Steps Real Level Memories
Microplex Output	3 Pin Mic Cable	3 Pin Mic Cable	3 Pin Mic Cable	3 Pin Mic Cable
DMX Output	N/A	5 Pin XLR	N/A	5 Pin XLR
Analog Output	N/A	(2 each) 8 Pin CJ Male	N/A	(1 each) 27 Pin CJ Male
Timed Fades	●	●	●	●
Blind Edit	●	●	●	●
Weight-lbs (approximate)	9	9	11	11
Height, Width, Depth (inches)	2.87 x 15.41 x 10.13	2.87 x 15.41 x 10.13	2.87 x 25.375 x 10.13	2.87 x 25.375 x 10.13

Full One Year Warranty For a period of one year from the date of sale, CAE, Inc. will replace any defective parts and will repair any defective module returned to the factory prepaid, without charge for parts or labor. Please consult your dealer for full warranty details.

© Copyright 1997 CAE Inc. All rights reserved. Publication #28-0037



CAE, Inc. • P.O. Box 430, 10087 Industrial Drive, Hamburg, Michigan 48139-0430 USA
 Phone (810) 231-9373 • Fax (810) 231-1631 • E-mail: lepsls@caeinc.com • www.caeinc.com