


**LUTRON®**  
**Product Report Card**


**Manufacturer:** Creative Systems Lighting –CSL

**Model Number Tested:** EDL-RM-27-4

**Other Model Numbers:** EDL-ADJ-27-4, EDL-NC-27-4, EDL-RM-30-4, EDL-ADJ-30-4, EDL-NC-30-4, EDL-RM-35-4, EDL-ADJ-35-4, EDL-NC-35-4, EDL-RM-40-4, EDL-ADJ-40-4, EDL-NC-40-4

#### Manufacturer's Description

Type of device: LED 29 W Downlight

Operating voltage: 120V

Input Power: 29.0 W

Input Current: 0.25 A

Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control

Dimming Range: Not Specified

Output Power: Not Specified

Lumen Output: Not Specified

Type/Shape: Downlight

Base Type: N/A

#### Lutron Test Results

Date Tested: 22-Jun-15

Test Voltage: 120 V

Test Notes: Performance verified with up to 5 fixtures per control. Test results valid only at 120 V and 60 Hz. Test results valid only with a ERP ESS030W-0700-42-CSL driver.

#### Lutron Recommended Products

*Lutron products not in this list can be considered to be not recommended, based on our testing.*

Product	Model Number	Control Type <sup>(1)</sup>	Fixtures per Dimmer <sup>(2)</sup>	Measured Dimming Range <sup>(3)</sup> (Software Trim Settings)		Perceived Low End <sup>(4)</sup>	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggle/ Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)*	FP	1 - 5	15%	99%	39%	Performance may vary with dimmers manufactured before 2013.
Maestro	MACL-153M ( )*	FP	1 - 5	10%	98%	32%	
Maestro Wireless	MRF2-6ELV	RP	1 - 5	10%	98%	31%	Load type not selectable.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 5	10%	97%	31%	
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 5	7%	97%	27%	
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 5	8%	98%	28%	
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 2	11% (9)	98% (99)	33%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 11	13% (10)	99% (85)	36%	Rating is per channel; total per module is 17.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 10	12% (14)	98% (82)	34%	Rating is per channel; total per module is 10.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 10	12% (13)	98% (80)	34%	Rating is per output; total quantity per Main Unit is 25.
Panel Module	GP (Harrier) Card	FP	1 - 10	8% (8)	99% (82)	29%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 10	12% (13)	98% (80)	34%	Rating is per output; total quantity per Main Unit is 15/18/25/25 for 2/3/4/6-Zone units, respectively.

HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V	RP	1 - 3	9% (8)	99% (90)	30%	Rating is per output; total quantity per Main Unit is 12.
<b>Residential Systems</b>							
RadioRA 2	RRD-6NA	RP	1 - 5	10%	98%	31%	
HomeWorks QS	HQRD-6NA	RP	1 - 5	10%	98%	31%	
HomeWorks	HxD-6ND	FP	1 - 2	11% (9)	98% (99)	33%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 11	13% (10)	99% (85)	36%	Rating is per channel; total per module is 17.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 10	12% (14)	98% (82)	34%	Rating is per channel; total per module is 10.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 10	12% (13)	98% (80)	34%	Rating is per output; total quantity per Main Unit is 25.
Panel Module	GP (Harrier) Card	FP	1 - 10	8% (8)	99% (82)	29%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 10	12% (13)	98% (80)	34%	Rating is per output; total quantity per Main Unit is 15/18/25/25 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 5	8%	98%	28%	
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 5	8%	98%	28%	
RadioRA 2	RRD-H6BRL (with neutral)	FP	1 - 3	9% (11)	97% (99)	30%	Installation with a neutral wire is required.
HomeWorks QS	HQRD-H6BRL (with neutral)	FP	1 - 3	9% (11)	97% (99)	30%	Installation with a neutral wire is required.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V	RP	1 - 3	9% (8)	99% (90)	30%	Rating is per output; total quantity per Main Unit is 12.
<b>Interfaces <sup>(5)</sup></b>							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 11	10% (13)	98% (81)	32%	
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 11	10%	98%	32%	
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; ( ) means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 5 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.