



LUTRON® Product Report Card

ID 1772

Manufacturer: Collingwood
Model Number Tested: DL282 WH NW DIM (with H5 500 T 38 NW driver)
Other Model Numbers: H2 PRO DLP38xxDIM, DLP60xxDIM, H4FF38xxxxDIM, H4FF60xxxxDIM, DL185xxxxDIM, DL282WHNWDIM, DL282WHWWDIM, DL284xxxxDIM, DL283xxxxDIM

Manufacturer's Description

Type of device:	<u>LED 8.5 W Downlight</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>240V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>8.5 W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>0.70 A</u>	Lumen Output:	<u>Not Specified</u>
Input Frequency:	<u>50 Hz/60 Hz</u>	Type/Shape:	<u>Downlight</u>
		Base Type:	<u>N/A</u>

Lutron Test Results

Date Tested: 28-Apr-15
 Test Voltage: 240 V
 Test Notes: Performance verified with up to 17 fixtures per control. Test results valid only at 240 V and 50 Hz.
 Test results valid only with a Collingwood 8.5W H2 Pro, H2 Pro 550, H4 FF, H4 eyeball, H5 500 TRIM or H5 500 SYM + ASYM driver.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
<i>No applicable results</i>							
<i>Commercial Systems</i>							
Panel Module	HW/LP-RPM-4U-230-CE	FP	1 - 54	7% (15)	100% (74)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per channel; total per module is 70.
Panel Module	GP (Harrier) Card	FP	1 - 54	7% (10)	100% (76)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output. Use load type 2-1.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family, 240V/ LQR-WPM-6PCE	FP	1 - 54	7% (15)	100% (77)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output; total quantity per Main Unit is 162/216/248 for 3/4/6-Zone units, respectively.
Grafik Eye/ HomeWorks	GRX-3104-CE/ HWI-WPM-6D-230CE	FP	1 - 39	9%	100%	31%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output; total quantity per Main Unit is 78/112/112/112 for 2/3/4/6-Zone units, respectively.
HomeWorks QS/ ESN Phase Adaptive	LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)*	RP	1 - 27	8% (16)	100% (81)	29%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per zone. Performance may vary with dimmers manufactured before March 2014.

<i>Residential Systems</i>							
Panel Module	HW/LP-RPM-4U-230-CE	FP	1 - 54	7% (15)	100% (74)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per channel; total per module is 70.
Panel Module	GP (Harrier) Card	FP	1 - 54	7% (10)	100% (76)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output. Use load type 2-1.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family, 240V/ LQR-WPM-6PCE	FP	1 - 54	7% (15)	100% (77)	27%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output; total quantity per Main Unit is 162/216/248 for 3/4/6-Zone units, respectively.
Grafik Eye/ HomeWorks	GRX-3104-CE/ HWI-WPM-6D-230CE	FP	1 - 39	9%	100%	31%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per output; total quantity per Main Unit is 78/112/112/112 for 2/3/4/6-Zone units, respectively.
HomeWorks QS/ ESN Phase Adaptive	LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)*	RP	1 - 27	8% (16)	100% (81)	29%	May experience buzzing and stepping dimming. High end and low end trim required. Rating is per zone. Performance may vary with dimmers manufactured before March 2014.
<i>Interfaces</i> ⁽⁵⁾							
	NGRX-ELVI-CE with Grafik Eye QS Main Unit, 240V	RP	1 - 9	6% (32)	100% (75)	25%	May experience buzzing and stepping dimming. High end and low end trim required.
	NGRX-PB-CE with Grafik Eye QS Main Unit, 240V	FP	1 - 9	8% (14)	100% (73)	29%	May experience buzzing and stepping dimming. High end and low end trim required.
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 17 fixtures per control. Test results valid only at 240 V and 50 Hz. Test results valid only with a Collingwood 8.5W H2 Pro, H2 Pro 550, H4 FF, H4 eyeball, H5 500 TRIM or H5 500 SYM + ASYM driver.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.

This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.