



LUTRON® Product Report Card

ID 2087

Manufacturer: Eaton
Model Number Tested: LS*6A20D010TE - E*6A20* - 6L*
Other Model Numbers: LS*6A15D010TE -*, LS*6A10D010TE-*

Manufacturer's Description

Type of device:	<u>LED 33.6 W Downlight</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>120V/277V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>33.6 W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>0.70 A</u>	Lumen Output:	<u>3000 lm</u>
Input Frequency:	<u>60 Hz/50 Hz</u>	Type/Shape:	<u>Downlight</u>
		Base Type:	<u>N/A</u>

Lutron Test Results

Date Tested: 15-Feb-16
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 4 fixtures per control. Test results valid only with a ESM040W-0800-42-CPL1 Driver and 1 lamp per Driver. Test results valid at 120V at 60Hz only.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)*	FP	1 - 4	19%	99%	43%	
Maestro	MACL-153M ()*	FP	1 - 4	9%	96%	29%	
Maestro Wireless	MRF2-6ND	FP	1 - 4	10%	100%	32%	
Maestro Wireless	MRF2-6ELV	RP	1 - 4	10%	99%	31%	Load type not selectable.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 4	6%	100%	25%	
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 4	4%	99%	21%	
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 4	4%	99%	20%	
Diva/ Ariadni	250W C-L dimmers (T5, T8)*	FP	1 - 7	19%	99%	43%	
Nova T*	NTCL-250 (T8)*	FP	1 - 7	19%	99%	43%	
Grafik T	GT-150 (T6)* without neutral	FP	1 - 4	19%	99%	44%	2 lamp minimum required without neutral. Low end adj for start time.
Grafik T	GTJ-150 (M6)* without neutral	FP	1 - 4	19%	99%	44%	2 lamp minimum required without neutral. Low end adj for start time.
Grafik T	GTJ-250M (M6)*/GT-250M (T7)* without neutral	FP	1 - 7	19%	99%	44%	2 lamp minimum required without neutral. Low end adj for start time.
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 5	10% (10)	99% (99)	31%	

Panel Module	HW/LP-RPM-4A-120	RP	1 - 25	13% (12)	100% (99)	36%	Low end adj for start time. Rating is per channel; total per module is 40.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 26	13% (16)	99% (99)	35%	Low end adj for start time. Rating is per channel; total per module is 26.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 19	9% (13)	98% (80)	30%	Rating is per output; total quantity per Main Unit is 47.
Panel Module	GP (Harrier) Card	FP	1 - 26	15% (15)	100% (99)	38%	Low end adj for start time. Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 19	9% (13)	98% (80)	30%	Rating is per output; total quantity per Main Unit is 28/35/47/47 for 2/3/4/6-Zone units, respectively.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V	RP	1 - 2	15% (12)	100% (99)	39%	Low end adj for start time. Rating is per output; total quantity per Main Unit is 8.
Residential Systems							
RadioRA 2	RRD-10ND	FP	1 - 4	10%	100%	32%	
HomeWorks QS	HQRD-6ND	FP	1 - 4	10%	100%	32%	
HomeWorks QS	HQRD-10ND	FP	1 - 4	10%	100%	32%	
RadioRA 2	RRD-6NA	RP	1 - 4	10%	99%	31%	
HomeWorks QS	HQRD-6NA	RP	1 - 4	10%	99%	31%	
HomeWorks	HxD-6ND	FP	1 - 5	10% (10)	99% (99)	31%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 25	13% (12)	100% (99)	36%	Low end adj for start time. Rating is per channel; total per module is 40.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 26	13% (16)	99% (99)	35%	Low end adj for start time. Rating is per channel; total per module is 26.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 19	9% (13)	98% (80)	30%	Rating is per output; total quantity per Main Unit is 47.
Panel Module	GP (Harrier) Card	FP	1 - 26	15% (15)	100% (99)	38%	Low end adj for start time. Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 19	9% (13)	98% (80)	30%	Rating is per output; total quantity per Main Unit is 28/35/47/47 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 4	4%	99%	20%	
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 4	4%	99%	20%	
RadioRA 2	RRD-6D	FP	1 - 4	4%	99%	21%	
RadioRA 2	RRD-H6BRL (with neutral)	FP	1 - 2	5% (8)	99% (99)	23%	Installation with a neutral wire is required.
HomeWorks QS	HQRD-H6BRL (with neutral)	FP	1 - 2	5% (8)	99% (99)	23%	Installation with a neutral wire is required.
RadioRA 2	RRT-G25LW (R3)* without neutral	FP	1 - 7	19%	99%	44%	2 lamp minimum required without neutral. Low end adj for start time.
HomeWorks QS	HQRT-G25LW (H2)* without neutral	FP	1 - 7	19%	99%	44%	2 lamp minimum required without neutral. Low end adj for start time.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V	RP	1 - 2	15% (12)	100% (99)	39%	Low end adj for start time. Rating is per output; total quantity per Main Unit is 8.
Interfaces ⁽⁵⁾							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 25	18% (21)	99% (65)	42%	Low end adj for start time.

	PHPM-WBX with 3-wire fluorescent control	RP	1 - 25	18%	99%	42%	Low end adj for start time.
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 4 fixtures per control.
Test results valid only with a ESM040W-0800-42-CPL1 Driver and 1 lamp per Driver.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.