



Product Report Card

Manufacturer: **Eaton**
Model Number Tested: **HLC4079301EWH**
 Other Model Numbers: HLC4079401EWH, HLC4079501EWH

Manufacturer's Description

Type of Device: <u>LED 12.6 W 4" Downlight</u>	Control Type: <u>Forward and Reverse Phase Control</u>
Operating Voltage: <u>120</u>	Dimming Range: <u>Not Specified</u>
Input Power: <u>12.6 W</u>	Output Power: <u>Not Specified</u>
Input Current: <u>0.106 A</u>	Lumen Output: <u>753 lm</u>
Input Frequency: <u>60 Hz</u>	Type/Shape: <u>4" Downlight</u>
	Base Type: <u>N/A</u>

Lutron Test Results

Date Tested 06/14/2019
 Test Voltage 120 V
 Test Notes Test results valid only at 120V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 17	10%	100%	32%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 85	10%	100%	32%	Manufacturer recommends RP only. Rating is per channel; total per module is 136.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 77	10%	100%	31%	Rating is per channel; total per module is 77.
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 57	10%	100%	32%	Rating is per channel; total quantity per Main Unit is 142.
Panel Module	GP (Harrier) Card	FP	1 - 77	10%	99%	31%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 57	10%	100%	32%	
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 120V, RP	RP	1 - 8	10%	100%	32%	Rating is per output; total quantity per Main Unit is 32.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 19	10%	100%	31%	
Vive	MRF2S-6ND	FP	1 - 11	10%	100%	32%	
Vive	MRF2S-6ELV	RP	1 - 11	10%	100%	32%	
Vive	MRF2S-6CL	FP	1 - 11	10%	95%	32%	

Interfaces

Power Modules	PHPM-PAwith Grafik Eye QS Main Unit	RP	1 - 137	10%	100%	32%	Manufacturer recommends RP only.
Power Modules	PHPM-WBXwith 3-wire fluorescent control	RP	1 - 137	10%	100%	32%	

Residential Systems

RadioRA 2	RRD-10ND	FP	1 - 11	10%	100%	32%	
HomeWorks QS	HQRD-6ND	FP	1 - 11	10%	100%	32%	
HomeWorks QS	HQRD-10ND	FP	1 - 11	10%	100%	32%	
RadioRA 2	RRD-6NA	RP	1 - 11	10%	100%	32%	Manufacturer recommends RP only.
HomeWorks QS	HQRD-6NA	RP	1 - 11	10%	100%	32%	
HomeWorks	HxD-6ND	FP	1 - 17	10%	100%	32%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 85	10%	100%	32%	Manufacturer recommends RP only. Rating is per channel; total per module is 136.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 77	10%	100%	31%	Rating is per channel; total per module is 77.
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 57	10%	100%	32%	Rating is per channel; total quantity per Main Unit is 142.
Panel Module	GP (Harrier) Card	FP	1 - 77	10%	99%	31%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 57	10%	100%	32%	
RadioRA 2	RRD-6CL (R3)	FP	1 - 11	10%	95%	32%	
HomeWorks QS	HQRD-6CL (H2)/HQRA-6CL (H2)	FP	1 - 11	10%	95%	32%	
RadioRA 2	RRT-G25LW (R3) without neutral	FP	1 - 19	10%	100%	31%	2 lamp minimum required without neutral.
HomeWorks QS	HQRT-G25LW (H2) without neutral	FP	1 - 19	10%	100%	31%	2 lamp minimum required without neutral.
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 120V, RP	RP	1 - 8	10%	100%	32%	Rating is per output; total quantity per Main Unit is 32.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 19	10%	100%	31%	
Homeworks QS	LQSE-4A-120-D, RP	RP	1 - 17	10%	100%	32%	
WallBox Dimmers							
Maestro	MACL-153M (TX)	FP	1 - 11	10%	100%	31%	
Maestro Wireless	MRF2-6ND	FP	1 - 11	10%	100%	32%	
Maestro Wireless	MRF2-6ELV	RP	1 - 11	10%	100%	32%	Load type not selectable.
Maestro Sensor	MSCL-OP153M (T2)/MSCL-VP153M (T2)	FP	1 - 11	10%	100%	32%	
Caseta Wireless	PD-6WCL (SD11)	FP	1 - 11	20%	100%	44%	
Maestro Wireless	MRF2-6CL (M6)	FP	1 - 11	10%	95%	32%	
Grafik T	GT-150 (T6) without neutral	FP	1 - 11	10%	100%	31%	2 lamp minimum required without neutral.
Grafik T	GTJ-150 (M6) without neutral	FP	1 - 11	10%	100%	31%	2 lamp minimum required without neutral.
Grafik T	GTJ-250M (M6)/GT-250M (T7) without neutral	FP	1 - 19	10%	100%	31%	2 lamp minimum required without neutral.
Caseta Wireless	PD-10NXD (SD11) without neutral	FP	1 - 19	20%	100%	44%	
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 19	10%	100%	31%	
Nova T*Reverse Phase LEDSlide to-off Dimmer	NTRP-250	RP	1 - 19	3%	100%	18%	
Caseta WirelessPhase Selectable	PD-5NE	RP	1 - 19	10%	100%	32%	
Caseta Wireless	PD-6WCL (SD12)	FP	1 - 11	10%	100%	32%	
Caseta Wireless	PD-10NXD (SD12) without neutral	FP	1 - 19	10%	100%	32%	
Maestro C•L Pro	MA-PRO without neutral	FP	1 - 19	10%	100%	32%	
Maestro C•L Pro	MA-PRO without neutral (default)	RP	1 - 19	10%	100%	32%	
Maestro C•L Pro	MA-PRO with neutral	FP	1 - 19	10%	100%	32%	
Maestro C•L Pro	MA-PRO with neutral	RP	1 - 19	10%	100%	32%	

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
Notes:	<ul style="list-style-type: none"> * Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information. (1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details. (2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control. (3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable. (4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook. (5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly. 						

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.

This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.