



LUTRON® Product Report Card

ID 2831

Manufacturer: Feit
Model Number Tested: CEPAR38/930/LED/2
Other Model Numbers: CEPAR38/930/2, PAR38/930/LEDG11, PAR38N/930/LEDG11, PAR38/830/LEDG11/CAN, PAR38/850/LEDG11, PAR38/830/LEDG11, PAR38/SP/LEDG10

Manufacturer's Description

| | | | |
|--------------------|-------------------------|----------------|--|
| Type of device: | <u>LED 15.5 W PAR38</u> | Control Type: | <u>Forward and Reverse Phase Control</u> |
| Operating voltage: | <u>120V</u> | Dimming Range: | <u>Not Specified</u> |
| Input Power: | <u>15.5 W</u> | Output Power: | <u>Not Specified</u> |
| Input Current: | <u>0.14 A</u> | Lumen Output: | <u>950 lm</u> |
| Input Frequency: | <u>60 Hz</u> | Type/Shape: | <u>PAR38</u> |
| | | Base Type: | <u>E26</u> |

Lutron Test Results

Date Tested: 17-Mar-17
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 9 fixtures per control.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

| Product | Model Number | Control Type ⁽¹⁾ | Fixtures per Dimmer ⁽²⁾ Min-Max | Measured Dimming Range ⁽³⁾ (Software Trim Settings) | | Perceived Low End ⁽⁴⁾ | Comments |
|---|--|-----------------------------|---|---|----------|----------------------------------|---|
| | | | | Low End | High End | | |
| <i>Wallbox Dimmers</i> | | | | | | | |
| Dival/ Skylark/ Skylark Contour/ Ariadni/ Toggle/ Lumea | C:L wall-mount dimmers (T8, T9)* | FP | 1 - 9 | 19% | 85% | 44% | Performance may vary with dimmers manufactured before 2013. |
| Dival/ Ariadni C250W | 250W C:L dimmers (T5,T8)* | FP | 1 - 16 | 19% | 85% | 44% | |
| Nova T* 250W | NTCL-250 (T8)* | FP | 1 - 16 | 19% | 85% | 44% | |
| Grafik T | Phase Selectable GT-5NEM/ GTJ-5NEM | RP | 1 - 16 | 17% | 94% | 41% | |
| <i>Commercial Systems</i> | | | | | | | |
| Panel Module | HW/LP-RPM-4A-120 | RP | 1 - 76 | 18% (15) | 94% (99) | 42% | Rating is per channel; total per module is 121. |
| Panel Module | HW/LP-RPM-4U-120 | FP | 1 - 31 | 18% (20) | 98% (99) | 43% | Rating is per channel; total per module is 31. |
| Panel Module | GP (Harrier) Card | FP | 1 - 31 | 19% (18) | 99% (99) | 43% | Rating is per output. Use load type 2-1. |
| HomeWorksQS/ myRoom | LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP | RP | 1 - 6 | 10% (15) | 97% (99) | 32% | Rating is per output; total quantity per Main Unit is 24. |
| Grafik T | Phase Selectable GT-5NEM/ GTJ-5NEM | RP | 1 - 16 | 17% | 94% | 41% | |
| <i>Residential Systems</i> | | | | | | | |

| | | | | | | | |
|----------------------------------|--|----|--------|----------|----------|-----|---|
| RadioRA 2 | RRD-10ND | FP | 1 - 9 | 14% | 92% | 38% | |
| HomeWorks QS | HQRD-10ND | FP | 1 - 9 | 14% | 92% | 38% | |
| Panel Module | HW/LP-RPM-4A-120 | RP | 1 - 76 | 18% (15) | 94% (99) | 42% | Rating is per channel; total per module is 121. |
| Panel Module | HW/LP-RPM-4U-120 | FP | 1 - 31 | 18% (20) | 98% (99) | 43% | Rating is per channel; total per module is 31. |
| Panel Module | GP (Harrier) Card | FP | 1 - 31 | 19% (18) | 99% (99) | 43% | Rating is per output. Use load type 2-1. |
| RadioRA 2 | Hybrid Keypad C.L RRD-HN6BRL | FP | 1 - 6 | 18% (22) | 92% (99) | 42% | Installation with a neutral wire is required. |
| HomeWorks QS | Hybrid Keypad C.L HQRD-HN6BRL | FP | 1 - 6 | 18% (22) | 92% (99) | 42% | Installation with a neutral wire is required. |
| HomeWorksQS/myRoom | LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 120V, RP | RP | 1 - 6 | 10% (15) | 97% (99) | 32% | Rating is per output; total quantity per Main Unit is 24. |
| Grafik T | Phase Selectable GT-5NEM/ GTJ-5NEM | RP | 1 - 16 | 17% | 94% | 41% | |
| Interfaces ⁽⁵⁾ | | | | | | | |
| | PHPM-PA with Grafik Eye QS Main Unit | RP | 1 - 76 | 19% (20) | 97% (99) | 44% | |
| | PHPM-WBX with 3-wire fluorescent control | RP | 1 - 76 | 19% | 97% | 44% | |
| Notes: | <p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p> | | | | | | |

Test Comments: Performance verified with up to 9 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.