

# REPORT CARD

(For fixtures using the Lutron  
Hi-lume® A-Series LED Driver)



## \*REQUIRED FIELDS

|                                   |  |
|-----------------------------------|--|
| <b>Manufacturer:*</b>             | Various Brands   |
| <b>Website:*</b>                  | See list of all High Performance LED Fixtures at <a href="http://www.lutron.com/findafixture">http://www.lutron.com/findafixture</a> |
| <b>Applicable model numbers:*</b> | See manufacturer-specific spec sheets for details  |
| <b>Date:*</b>                     |  |

| Fixture manufacturer's description |                                     |  |   |
|------------------------------------|-------------------------------------|--|---|
| Type of fixture:*                  | Choose from list at right ►         | <input checked="" type="checkbox"/> Cove/Strip light | <input checked="" type="checkbox"/> Pucklight       |
| Operating voltage:                 | 120V                                | <input checked="" type="checkbox"/> Downlight        | <input checked="" type="checkbox"/> Sconce          |
| Control type:                      | 2-wire forward phase (with neutral) | <input checked="" type="checkbox"/> Linear LEDs      | <input checked="" type="checkbox"/> Troffer fixture |
| Dimming range:                     | 100% – 1%                           | <input checked="" type="checkbox"/> Light engine     | <input checked="" type="checkbox"/> Wallwash        |
| Input power (max.):*               | Varies                              | <input checked="" type="checkbox"/> Pendant          |   |

|  |
|--|
| <b>Driver manufacturer:</b> Lutron Electronics |
| <b>Product:</b> Hi-lume A-Series LED driver    |



## Compatible Lutron products

| Product family  | Part number                     | Fixtures per dimmer (120V only)* | Measured light output range |
|---|---------------------------------|----------------------------------|-----------------------------|
| NovaT☆®   | NTLV-600-CPN0199                | 1 – 8                            | 100% – 1%                   |
| Maestro Wireless®   | MRF2-6ND-120                    | 1 – 8                            | 100% – 1%                   |
| RadioRA® 2  | 1000W RRD-10ND                  | 1 – 13                           | 100% – 1%                   |
| RadioRA 2 adaptive dimmer                                       | RRD-6NA                         | 1 – 8                            | 100% – 1%                   |
| RadioRA 600W  | RA-6ND                          | 1 – 8                            | 100% – 1%                   |
| RadioRA 1000W   | RA-10ND                         | 1 – 13                           | 100% – 1%                   |
| HomeWorks® QS 600W  | HQRD-6ND                        | 1 – 8                            | 100% – 1%                   |
| HomeWorks QS 1000W  | HQRD-10ND                       | 1 – 13                           | 100% – 1%                   |
| HomeWorks QS adaptive dimmer                                    | HQRD-6NA                        | 1 – 8                            | 100% – 1%                   |
| HomeWorks QS WPM  | HQRJ-WPM-6D-120                 | 1 – 11<br>(per output)           | 100% – 1%                   |
| HomeWorks 600W dimmer   | HRD-6ND                         | 1 – 8                            | 100% – 1%                   |
| HomeWorks 1000W dimmer  | HWD-10ND,<br>HRD-10ND           | 1 – 8                            | 100% – 1%                   |
| HomeWorks WPM   | HWI-WPM-6D-120                  | 1 – 10<br>(per output)           | 100% – 1%                   |
| GRAFIK Eye® QS  | QSGR-,<br>QSGRJ-                | 1 – 10<br>(per output)           | 100% – 1%                   |
| GRAFIK Eye 3000   | GRX-3100,<br>GRX-3500           | 1 – 10<br>(per output)           | 100% – 1%                   |
| RPM-4U module,<br>(LCP, HomeWorks,<br>GRAFIK Systems, Quantum®) | HW-RPM-4U-120,<br>LP-RPM-4U-120 | 1 – 26<br>(per output)           | 100% – 1%                   |
| RPM-4A module<br>(LCP, HomeWorks,<br>GRAFIK Systems, Quantum)   | HW-RPM-4A-120,<br>LP-RPM-4A-120 | 1 – 8<br>(per output)            | 100% – 1%                   |
| GP panels<br>(LCP, HomeWorks,<br>GRAFIK Systems, Quantum)       | Various                         | 1 – 27                           | 100% – 1%                   |
| Stanza®   | SZ-6ND                          | 1 – 8                            | 100% – 1%                   |

\* Fixtures per dimmer value assumes a 40W fixture. Number of fixtures may be higher if wattage is less than 40W.

NOTE: Contact Lutron tech support for degangng rules when using wallbox controls on the Hi-lume A-Series LED Driver.