



LUTRON® Product Report Card

ID 1515

Manufacturer: Philips
Model Number Tested: 9290002329
 Other Model Numbers: 451856, BC8PAR20/AMB/3000 DIM 120V

Manufacturer's Description

Type of device:	<u>LED 8 W PAR20</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>120V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>8.0 W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>0.08 A</u>	Lumen Output:	<u>470 lm</u>
Input Frequency:	<u>60 Hz</u>	Type/Shape:	<u>PAR20</u>
		Base Type:	<u>E26</u>

Lutron Test Results

Date Tested: 22-Aug-14
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 18 fixtures per control. Test results valid only at 120 V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C-L wall-mount dimmers (T1, T4)*	FP	1 - 18	5%	99%	22%	May experience buzzing. Performance may vary with dimmers manufactured before 2013.
Maestro	MACL-153M ()*	FP	1 - 18	4%	94%	20%	May experience buzzing.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 18	2%	100%	16%	May experience buzzing.
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 18	4%	96%	19%	May experience buzzing.
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 18	2%	98%	15%	May experience buzzing.
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 8	4% (30)	99% (99)	19%	May experience buzzing.
Panel Module	HW/LP-RPM-4A-120	RP	1 - 14	5% (30)	92% (99)	22%	May experience buzzing. Rating is per channel; total per module is 22.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 36	5% (30)	99% (85)	22%	May experience buzzing. Rating is per channel; total per module is 36.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 36	3% (25)	100% (82)	16%	May experience buzzing. Rating is per output; total quantity per Main Unit is 90.
Panel Module	GP (Harrier) Card	FP	1 - 26	6% (32)	100% (88)	24%	May experience buzzing. Rating is per output. Use load type 2-1.

Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D- 120	FP	1 - 36	3% (25)	100% (82)	16%	May experience buzzing. Rating is per output; total quantity per Main Unit is 54/67/90/90 for 2/3/4/6-Zone units, respectively.
Residential Systems							
HomeWorks	HxD-6ND	FP	1 - 8	4% (30)	99% (99)	19%	May experience buzzing.
Panel Module	HW/LP-RPM-4A- 120	RP	1 - 14	5% (30)	92% (99)	22%	May experience buzzing. Rating is per channel; total per module is 22.
Panel Module	HW/LP-RPM-4U- 120	FP	1 - 36	5% (30)	99% (85)	22%	May experience buzzing. Rating is per channel; total per module is 36.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 36	3% (25)	100% (82)	16%	May experience buzzing. Rating is per output; total quantity per Main Unit is 90.
Panel Module	GP (Harrier) Card	FP	1 - 26	6% (32)	100% (88)	24%	May experience buzzing. Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D- 120	FP	1 - 36	3% (25)	100% (82)	16%	May experience buzzing. Rating is per output; total quantity per Main Unit is 54/67/90/90 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 18	2%	98%	15%	May experience buzzing.
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 18	2%	98%	15%	May experience buzzing.
Interfaces ⁽⁵⁾							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 14	2% (20)	100% (86)	15%	May experience buzzing.
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 14	2%	100%	15%	May experience buzzing.
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 18 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.