



LUTRON® Product Report Card

ID 1565

Manufacturer: Osram Sylvania
Model Number Tested: 79644 LED10A19/DIM/CL/O/827/RP
Other Model Numbers: 79644 LED10A19/DIM/CL/O/827/G3/BL, 79147 LED10A19/DIM/CL/O/827/BL, 79145 LED10A19/DIM/O/850/G4/BL, 79143 LED10A19/DIM/O/827/G4/BL, 79144 LED10A19/DIM/O/850/G4, 79146 LED10A19/DIM/CL/O/827, 79142 LED10A19/DIM/O/827/G4

Manufacturer's Description

Type of device:	<u>LED 10.5W A19</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>120V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>10.5 W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>0.09 A</u>	Lumen Output:	<u>800 lm</u>
Input Frequency:	<u>60 Hz</u>	Type/Shape:	<u>A19</u>
		Base Type:	<u>E26</u>

Lutron Test Results

Date Tested: 29-Sep-14
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 20 fixtures per control. Test results valid only at 120 V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C-L wall-mount dimmers (T1, T4)*	FP	1 - 14	9%	87%	30%	
Maestro	MACL-153M ()*	FP	1 - 14	7%	85%	26%	
Credenza	TTCL-100	FP	1 - 9	11%	89%	33%	Performance verified with up to 5 fixtures.
Maestro Wireless	MRF2-6ND	FP	1 - 14	5%	90%	23%	
Maestro Wireless	MRF2-6ELV	RP	1 - 14	5%	90%	22%	Load type not selectable.
Maestro Wireless	MRF2-3LD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
Maestro Wireless	MRF2-3PD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 14	6%	85%	24%	
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 14	5%	85%	22%	
Caseta Wireless	PD-3PCL (SD11)*	FP	1 - 9	6%	86%	25%	Performance verified with up to 5 fixtures.
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 14	6%	85%	24%	
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 18	6% (13)	89% (99)	25%	
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 76	6% (13)	97% (99)	25%	Rating is per output; total quantity per Main Unit is 190.
Panel Module	GP (Harrier) Card	FP	1 - 59	7% (12)	93% (99)	27%	Rating is per output. Use load type 2-1.

Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D- 120	FP	1 - 76	6% (13)	97% (99)	25%	Rating is per output; total quantity per Main Unit is 114/142/190/190 for 2/3/4/6-Zone units, respectively.
Residential Systems							
RadioRA 2	RRD-10ND	FP	1 - 14	5%	90%	23%	
HomeWorks QS	HQRD-6ND	FP	1 - 14	5%	90%	23%	
HomeWorks QS	HQRD-10ND	FP	1 - 14	5%	90%	23%	
RadioRA 2	RRD-6NA	RP	1 - 14	5%	90%	22%	
HomeWorks QS	HQRD-6NA	RP	1 - 14	5%	90%	22%	
HomeWorks	HxD-6ND	FP	1 - 18	6% (13)	89% (99)	25%	
RadioRA 2	RRD-3LD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
HomeWorks QS	HQR-3LD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
RadioRA 2	RRD-3PD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
HomeWorks QS	HQR-3PD	FP	1 - 9	5%	91%	22%	Performance verified with up to 5 fixtures.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 76	6% (13)	97% (99)	25%	Rating is per output; total quantity per Main Unit is 190.
Panel Module	GP (Harrier) Card	FP	1 - 59	7% (12)	93% (99)	27%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D- 120	FP	1 - 76	6% (13)	97% (99)	25%	Rating is per output; total quantity per Main Unit is 114/142/190/190 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 14	6%	85%	24%	
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 14	6%	85%	24%	
Interfaces ⁽⁵⁾							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 119	6% (14)	97% (99)	25%	
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 119	6%	97%	25%	
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 20 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.