



LUTRON® Product Report Card

ID 1780

Manufacturer: Westinghouse
Model Number Tested: 33014
Other Model Numbers: 33064 (BR40)

Manufacturer's Description

Type of device: LED 17W PAR38
 Operating voltage: 120V
 Input Power: 17.0 W
 Input Current: 0.15 A
 Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control
 Dimming Range: Not Specified
 Output Power: Not Specified
 Lumen Output: 1200 lm
 Type/Shape: PAR38
 Base Type: E26

Lutron Test Results

Date Tested: 22-Apr-15
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 9 fixtures per control. Test results valid only at 120 V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
			Min-Max	Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C-L wall-mount dimmers (T1, T4, T8)*	FP	1 - 8	5%	96%	22%	Performance may vary with dimmers manufactured before 2013.
Maestro	MACL-153M (L)*	FP	1 - 8	5%	85%	22%	
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 8	5%	86%	22%	Low end trim required.
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 8	4%	87%	20%	Low end trim required.
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 8	5%	87%	21%	Low and high end trim required.
Diva/ Ariadni	250W C•L dimmers (T5)*	FP	1 - 14	5%	96%	22%	Low end trim required.
Nova T*	NTCL-250 (T8)*	FP	1 - 14	5%	96%	22%	Low end trim required.
Grafik T	GT-150 (T6)* without neutral	FP	1 - 8	7%	100%	27%	2 lamp minimum required without neutral. Low and high end trim required.
Grafik T	GTJ-150 (M6)* without neutral	FP	1 - 8	7%	100%	27%	2 lamp minimum required without neutral. Low and high end trim required.
Grafik T	GTJ-250M (M6)* GT-250M (T7)* without neutral	FP	1 - 14	7%	100%	27%	2 lamp minimum required without neutral. Low and high end trim required.
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 11	6% (35)	92% (92)	24%	Low and high end trim required.
Panel Module	HW/LP-RPM-4A-120	RP	1 - 9	6% (26)	100% (85)	25%	Rating is per channel; total per module is 14.

Panel Module	HW/LP-RPM-4U-120	FP	1 - 61	9% (36)	100% (78)	31%	Low and high end trim required. Rating is per channel; total per module is 61.
Panel Module	GP (Harrier) Card	FP	1 - 61	6% (27)	100% (99)	24%	Low and high end trim required. Rating is per output. Use load type 2-1.
Residential Systems							
HomeWorks	HxD-6ND	FP	1 - 11	6% (35)	92% (92)	24%	Low and high end trim required.
Panel Module	HW/LP-RPM-4A-120	RP	1 - 9	6% (26)	100% (85)	25%	Rating is per channel; total per module is 14.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 61	9% (36)	100% (78)	31%	Low and high end trim required. Rating is per channel; total per module is 61.
Panel Module	GP (Harrier) Card	FP	1 - 61	6% (27)	100% (99)	24%	Low and high end trim required. Rating is per output. Use load type 2-1.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 8	5%	87%	21%	Low and high end trim required.
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 8	5%	87%	21%	Low and high end trim required.
RadioRA 2	RRT-G25LW (R3)* without neutral	FP	1 - 14	7%	100%	27%	2 lamp minimum required without neutral. Low and high end trim required.
HomeWorks QS	HQRT-G25LW (H2)* without neutral	FP	1 - 14	7%	100%	27%	2 lamp minimum required without neutral. Low and high end trim required.
Interfaces ⁽⁵⁾							
<i>No applicable results</i>							
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 9 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.