

[No Product Image available]


**LUTRON®**  
**Product Report Card**

ID 3060

**Manufacturer:** Philips  
**Model Number Tested:** 9290013156  
**Other Model Numbers:** None

**Manufacturer's Description**

Type of device: LED 8.5 W A19  
 Operating voltage: 120V  
 Input Power: 8.5 W  
 Input Current: 0.09 A  
 Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control  
 Dimming Range: Not Specified  
 Output Power: Not Specified  
 Lumen Output: 800 lm  
 Type/Shape: A19  
 Base Type: E26

**Lutron Test Results**

Date Tested: 17-Aug-17  
 Test Voltage: 120 V  
 Test Notes: Performance verified with up to 17 fixtures per control. Test results valid only at 120 V and 60 Hz.

**Lutron Recommended Products**

*Lutron products not in this list can be considered to be not recommended, based on our testing.*

Product	Model Number	Control Type <sup>(1)</sup>	Fixtures per Dimmer <sup>(2)</sup>		Measured Dimming Range <sup>(3)</sup> (Software Trim Settings)		Perceived Low End <sup>(4)</sup>	Comments
			Min-Max	Low End	High End			
<i>Wallbox Dimmers</i>								
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggle/ Lumea	C·L wall-mount dimmers (T8, T9)*	FP	1 - 17	5%	90%	22%	Performance may vary with dimmers manufactured before 2013.	
Maestro	MACL-153M (TX)*	FP	1 - 17	4%	91%	20%		
Maestro Wireless	MRF2-6ND	FP	1 - 17	9%	88%	30%		
Maestro Wireless	MRF2-6ELV	RP	1 - 17	6%	91%	24%	Load type not selectable.	
Maestro Wireless	MRF2-3LD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.	
Maestro Wireless	MRF2-3PD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.	
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 17	5%	91%	21%		
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 17	4%	91%	19%		
Caseta Wireless	PD-3PCL (SD11)*	FP	1 - 11	3%	88%	18%	Performance verified with up to 4 fixtures.	
Diva/ Ariadni C250W	250W C·L dimmers (T5, T8)*	FP	1 - 29	5%	90%	22%		
Nova T* 250W	NTCL-250 (T8)*	FP	1 - 29	5%	90%	22%		
Grafik T	GT-150 (T6)* without neutral	FP	1 - 17	9%	88%	30%	2 lamp minimum required without neutral.	
Grafik T	GTJ-150 (M6)* without neutral	FP	1 - 17	9%	88%	30%	2 lamp minimum required without neutral.	

Grafik T	GTJ-250M (M6)*/GT-250M (T7)* without neutral	FP	1 - 29	9%	88%	30%	2 lamp minimum required without neutral.
Caseta Wireless	PD-10NXD (SD11)* without neutral	FP	1 - 29	4%	91%	19%	
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 29	3%	92%	17%	
Skylark Contour Slide to-off	CTCL-150	FP	1 - 17	5%	90%	22%	
Caseta Wireless Phase Selectable	PD-5NE	RP	1 - 29	4%	88%	20%	
<b>Commercial Systems</b>							
Stanza	SZ-6ND	FP	1 - 41	3% (15)	88% (99)	17%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 120	3% (22)	88% (99)	16%	Rating is per channel; total per module is 192.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 187	4% (24)	88% (99)	19%	Rating is per channel; total per module is 187.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 79	4% (25)	88% (99)	19%	Rating is per output; total quantity per Main Unit is 197.
Panel Module	GP (Harrier) Card	FP	1 - 187	2% (20)	90% (99)	14%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 79	4% (25)	88% (99)	19%	Rating is per output; total quantity per Main Unit is 118/148/197/197 for 2/3/4/6-Zone units, respectively.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 12	4% (22)	89% (99)	19%	Rating is per output; total quantity per Main Unit is 48.
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 29	3%	92%	17%	
Vive	MRF2S-6ND	FP	1 - 17	9%	88%	30%	
Vive	MRF2S-6ELV	RP	1 - 17	6%	91%	24%	
<b>Residential Systems</b>							
RadioRA 2	RRD-10ND	FP	1 - 17	9%	88%	30%	
HomeWorks QS	HQRD-6ND	FP	1 - 17	9%	88%	30%	
HomeWorks QS	HQRD-10ND	FP	1 - 17	9%	88%	30%	
RadioRA 2	RRD-6NA	RP	1 - 17	6%	91%	24%	
HomeWorks QS	HQRD-6NA	RP	1 - 17	6%	91%	24%	
HomeWorks	HxD-6ND	FP	1 - 41	3% (15)	88% (99)	17%	
RadioRA 2	RRD-3LD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.
HomeWorks QS	HQR-3LD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.
RadioRA 2	RRD-3PD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.
HomeWorks QS	HQR-3PD	FP	1 - 11	5%	87%	23%	Performance verified with up to 5 fixtures.
Panel Module	HW/LP-RPM-4A-120	RP	1 - 120	3% (22)	88% (99)	16%	Rating is per channel; total per module is 192.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 187	4% (24)	88% (99)	19%	Rating is per channel; total per module is 187.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 79	4% (25)	88% (99)	19%	Rating is per output; total quantity per Main Unit is 197.
Panel Module	GP (Harrier) Card	FP	1 - 187	2% (20)	90% (99)	14%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 79	4% (25)	88% (99)	19%	Rating is per output; total quantity per Main Unit is 118/148/197/197 for 2/3/4/6-Zone units, respectively.

RadioRA 2	Hybrid Keypad C.L RRD- HN6BRL	FP	1 - 11	6%	89%	25%	Installation with a neutral wire is required.
HomeWorks QS	Hybrid Keypad C.L HQRD- HN6BRL	FP	1 - 11	6%	89%	25%	Installation with a neutral wire is required.
RadioRA 2	RRT-G25LW (R3)* without neutral	FP	1 - 29	9%	88%	30%	2 lamp minimum required without neutral.
HomeWorks QS	HQRT-G25LW (H2)* without neutral	FP	1 - 29	9%	88%	30%	2 lamp minimum required without neutral.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 12	4% (22)	89% (99)	19%	Rating is per output; total quantity per Main Unit is 48.
Grafik T	Phase Selectable GT- 5NEM/ GTJ- 5NEM	RP	1 - 29	3%	92%	17%	
<b>Interfaces<sup>(5)</sup></b>							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 192	5% (26)	88% (99)	22%	
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 192	5%	88%	22%	
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; ( ) means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 17 fixtures per control.

*For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.*

*This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at [www.lutron.com/LEDtool](http://www.lutron.com/LEDtool).*