



ID: 3129

## Product Report Card

**Manufacturer:** Ansell Lighting

**Model Number Tested:** APRILED/CW

Other Model Numbers:

### Manufacturer's Description

Type of Device: LED 8 W Downlight

Operating Voltage: 230V

Input Power: 8 W

Input Current: Not Specified

Input Frequency: 50 Hz

Control Type: Forward and Reverse Phase Control

Dimming Range: Not Specified

Output Power: 8 W

Lumen Output: 567 lm

Type/Shape: Downlight

Base Type: N/A

### Lutron Test Results

Date Tested: 10/19/2017

Test Voltage: 240 V

Test Notes

### Lutron Recommended Products

*Lutron products not in this list can be considered to be not recommended, based on our testing.*

Product	Model Number	Control Type <sup>(1)</sup>	Fixtures per Dimmer <sup>(2)</sup>	Measured Dimming Range <sup>(3)</sup> (Software Trim Settings)		Perceived Low End <sup>(4)</sup>	Comments
			Min-Max	Low End	High End		
<i>Commercial Systems</i>							
Panel Module	HW/LP-RPM-4A-230	FP	1 - 42	1%	99%	10%	
Panel Module	HW/LP-RPM-4U-230-CE	FP	1 - 76	1%	99%	10%	
Panel Module	GP (Harrier) Card	FP	1 - 60	7%	98%	26%	
Grafik Eye/HomeWorks	GRX-3104-CE/HWI-WPM-6D-230CE	FP	1 - 60	8%	98%	29%	

Product	Model Number	Control Type	Fixtures per Dimmer	Measured Dimming Range (Software Trim Settings)		Perceived Low End	Comments
			Min-Max	Low End	High End		
HomeWorks QS/ESN Phase Adaptive	LQSE-4A-D (Gen. 2)/QSNE-4A-D (Gen. 2)	RP	1 - 62	5%	99%	21%	
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP	RP	1 - 18	8%	98%	28%	
Grafik Integrale	GXI-3104	RP	1 - 56	10%	98%	31%	

### Interfaces

[none]	NGRX-ELVI-CE with Grafik Eye QS Main Unit, 240V	RP	1 - 87	6%	98%	25%	PRODUCT SPECIFIC TESTING: 10 sec fade: + >>>>1f/min load <<<< >>>>full load<<<<
[none]	NGRX-PB-CE with Grafik Eye QS Main Unit, 240V	FP	1 - 13	3%	99%	17%	PRODUCT SPECIFIC TESTING: 10 sec fade: +

### Residential Systems

Panel Module	HW/LP-RPM-4A-230	FP	1 - 42	1%	99%	10%	
Panel Module	HW/LP-RPM-4U-230-CE	FP	1 - 76	1%	99%	10%	
Panel Module	GP (Harrier) Card	FP	1 - 60	7%	98%	26%	
Rania	RNDU-252B	RP	1 - 31	5%	91%	23%	
Grafik Eye/HomeWorks	GRX-3104-CE/HWI-WPM-6D-230CE	FP	1 - 60	8%	98%	29%	
HomeWorks QS/ESN Phase Adaptive	LQSE-4A-D (Gen. 2)/QSNE-4A-D (Gen. 2)	RP	1 - 62	5%	99%	21%	
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP	RP	1 - 18	8%	98%	28%	

### WallBox Dimmers

No applicable results

Notes:	<ul style="list-style-type: none"> <li>* Identical model numbers with different compatibility codes may have different performance; ( ) means there is no compatibility code assigned; contact technical support for additional information.</li> <li>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</li> <li>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</li> <li>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</li> <li>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</li> <li>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</li> </ul>
--------	---

*For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or [leds@lutron.com](mailto:leds@lutron.com).*

*This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at [www.lutron.com/LEDtool](http://www.lutron.com/LEDtool).*

---