

[No Product Image available]


LUTRON®
Product Report Card

ID 3102

Manufacturer: Aurora
Model Number Tested: AR-AL3340/30-120V
Other Model Numbers: None

Manufacturer's Description

Type of device: LED 9 W Downlight
 Operating voltage: 120V
 Input Power: 9.0 W
 Input Current: 0.07 A
 Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control
 Dimming Range: Not Specified
 Output Power: Not Specified
 Lumen Output: 600 lm
 Type/Shape: Downlight
 Base Type: E26

Lutron Test Results

Date Tested: 12-Sep-17
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 16 fixtures per control.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾ Min-Max	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
				Low End	High End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C-L wall-mount dimmers (T8, T9)*	FP	1 - 16	8%	96%	28%	Performance may vary with dimmers manufactured before 2013.
Maestro	MACL-153M (TX)*	FP	1 - 16	7%	94%	27%	
Maestro Wireless	MRF2-6ND	FP	1 - 16	14%	96%	37%	
Maestro Wireless	MRF2-6ELV	RP	1 - 16	15%	94%	38%	Load type not selectable.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 16	12%	95%	34%	
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 16	17%	95%	41%	
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 16	12%	94%	35%	
Diva/ Ariadni C250W	250W C-L dimmers (T5, T8)*	FP	1 - 27	8%	96%	28%	
Nova T* 250W	NTCL-250 (T8)*	FP	1 - 27	8%	96%	28%	
Grafik T	GT-150 (T6)* without neutral	FP	1 - 16	17%	95%	41%	2 lamp minimum required without neutral.
Grafik T	GTJ-150 (M6)* without neutral	FP	1 - 16	17%	95%	41%	2 lamp minimum required without neutral.
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 27	11%	95%	34%	

Diva/ Skylark Contour Reverse Phase LED Preset Dimmers	DVRP-253P CTRP-253P	RP	1 - 27	2%	93%	15%	
Skylark Contour Slide to-off	CTCL-150	FP	1 - 16	8%	96%	28%	
Caseta Wireless Phase Selectable	PD-5NE	RP	1 - 27	12%	95%	34%	
Commercial Systems							
Stanza	SZ-6ND	FP	1 - 9	12% (20)	94% (99)	35%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 123	12% (24)	94% (99)	34%	Rating is per channel; total per module is 196.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 44	11% (25)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 110.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 44	11% (25)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 66/82/110/110 for 2/3/4/6-Zone units, respectively.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 12	13% (24)	95% (99)	36%	Rating is per output; total quantity per Main Unit is 48.
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 27	11%	95%	34%	
Vive	MRF2S-6ND	FP	1 - 16	14%	96%	37%	
Vive	MRF2S-6ELV	RP	1 - 16	15%	94%	38%	
Vive	MRF2S-6CL	FP	1 - 16	12%	94%	35%	
Residential Systems							
RadioRA 2	RRD-10ND	FP	1 - 16	14%	96%	37%	
HomeWorks QS	HQRD-6ND	FP	1 - 16	14%	96%	37%	
HomeWorks QS	HQRD-10ND	FP	1 - 16	14%	96%	37%	
RadioRA 2	RRD-6NA	RP	1 - 16	15%	94%	38%	
HomeWorks QS	HQRD-6NA	RP	1 - 16	15%	94%	38%	
HomeWorks	HxD-6ND	FP	1 - 9	12% (20)	94% (99)	35%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 123	12% (24)	94% (99)	34%	Rating is per channel; total per module is 196.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 44	11% (25)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 110.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 44	11% (25)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 66/82/110/110 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 16	12%	94%	35%	
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 16	12%	94%	35%	
RadioRA 2	Hybrid Keypad C.L RRD- HN6BRL	FP	1 - 11	12%	95%	35%	Installation with a neutral wire is required.
HomeWorks QS	Hybrid Keypad C.L HQRD- HN6BRL	FP	1 - 11	12%	95%	35%	Installation with a neutral wire is required.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 12	13% (24)	95% (99)	36%	Rating is per output; total quantity per Main Unit is 48.
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 27	11%	95%	34%	

Homeworks QS	LQSE-4A-120-D, FP	FP	1 - 12	8% (20)	95% (99)	28%	
Homeworks QS	LQSE-4A-120-D, RP	RP	1 - 25	12% (20)	96% (99)	34%	
<i>Interfaces</i> ⁽⁵⁾							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 140	9% (25)	97% (99)	30%	
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 140	9%	97%	30%	
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>						

Test Comments: Performance verified with up to 16 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.