



LUTRON® Product Report Card

ID 2544

Manufacturer: Eaton
Model Number Tested: RL560WH9927
Other Model Numbers: RL560WH9930, RL560WH9935, RL560WH9940, RL560WH9950

Manufacturer's Description

Type of device:	<u>LED 13.5 W Retrofit Downlight</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>120V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>13.5 W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>0.16 A</u>	Lumen Output:	<u>900 lm</u>
Input Frequency:	<u>60 Hz</u>	Type/Shape:	<u>Retrofit Downlight</u>
		Base Type:	<u>E26</u>

Lutron Test Results

Date Tested: 24-Oct-16
 Test Voltage: 120 V
 Test Notes: Performance verified with up to 11 fixtures per control. Test results valid only at 120 V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
				Min-Max	Low End		
<i>Wallbox Dimmers</i>							
Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea	C•L wall-mount dimmers (T8, T9)*	FP	1 - 11	11%	97%	34%	Performance may vary with dimmers manufactured before 2013.
Maestro	MACL-153M (L)*	FP	1 - 11	11%	90%	33%	
Maestro Wireless	MRF2-6ELV	RP	1 - 11	8%	97%	29%	Load type not selectable.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	FP	1 - 11	8%	92%	29%	
Caseta Wireless	PD-6WCL (SD11)*	FP	1 - 11	13%	94%	36%	
Maestro Wireless	MRF2-6CL (M6)*	FP	1 - 11	9%	95%	31%	
Diva/ Ariadni C250W	250W C•L dimmers (T5, T8)*	FP	1 - 18	11%	97%	34%	
Nova T* 250W	NTCL-250 (T8)*	FP	1 - 18	11%	97%	34%	
Grafik T	GT-150 (T6)* without neutral	FP	1 - 11	8%	98%	29%	2 lamp minimum required without neutral.
Grafik T	GTJ-150 (M6)* without neutral	FP	1 - 11	8%	98%	29%	2 lamp minimum required without neutral.
Grafik T	Phase Selectable GT-5NEM/ GTJ-5NEM	RP	1 - 18	11%	97%	34%	
<i>Commercial Systems</i>							
Stanza	SZ-6ND	FP	1 - 6	8% (14)	98% (99)	29%	

Panel Module	HW/LP-RPM-4A-120	RP	1 - 66	8% (18)	96% (99)	29%	Rating is per channel; total per module is 105.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 30	8% (23)	99% (99)	29%	Rating is per channel; total per module is 30.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 30	11% (26)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 75.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 30	11% (26)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 45/56/75/75 for 2/3/4/6-Zone units, respectively.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 6	11% (21)	99% (99)	33%	Rating is per output; total quantity per Main Unit is 24.
Grafik T	Phase Selectable GT- 5NEM/ GTJ- 5NEM	RP	1 - 18	11%	97%	34%	
Residential Systems							
RadioRA 2	RRD-6NA	RP	1 - 11	8% (25)	97% (99)	29%	
HomeWorks QS	HQRD-6NA	RP	1 - 11	8% (25)	97% (99)	29%	
HomeWorks	HxD-6ND	FP	1 - 6	8% (14)	98% (99)	29%	
Panel Module	HW/LP-RPM-4A-120	RP	1 - 66	8% (18)	96% (99)	29%	Rating is per channel; total per module is 105.
Panel Module	HW/LP-RPM-4U-120	FP	1 - 30	8% (23)	99% (99)	29%	Rating is per channel; total per module is 30.
Grafik QS/ Wallbox Power Module	Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P	FP	1 - 30	11% (26)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 75.
Grafik Eye 3000/ HomeWorks	Grafik Eye 3000 Family/ HWI-WPM-6D-120	FP	1 - 30	11% (26)	98% (99)	34%	Rating is per output; total quantity per Main Unit is 45/56/75/75 for 2/3/4/6-Zone units, respectively.
RadioRA 2	RRD-6CL (R3)*	FP	1 - 11	9% (30)	95% (99)	31%	
HomeWorks QS	HQRD-6CL (H2)*/ HQRA-6CL (H2)*	FP	1 - 11	9% (30)	95% (99)	31%	
RadioRA 2	Hybrid Keypad C.L RRD- HN6BRL	FP	1 - 7	7% (25)	99% (99)	27%	Installation with a neutral wire is required.
HomeWorks QS	Hybrid Keypad C.L HQRD- HN6BRL	FP	1 - 7	7% (25)	99% (99)	27%	Installation with a neutral wire is required.
HomeWorksQS/ myRoom	LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP	RP	1 - 6	11% (21)	99% (99)	33%	Rating is per output; total quantity per Main Unit is 24.
Grafik T	Phase Selectable GT- 5NEM/ GTJ- 5NEM	RP	1 - 18	11%	97%	34%	
Interfaces⁽⁵⁾							
	PHPM-PA with Grafik Eye QS Main Unit	RP	1 - 97	8% (23)	98% (99)	29%	
	PHPM-WBX with 3-wire fluorescent control	RP	1 - 97	8%	98%	29%	

Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p>
--------	--

Test Comments: Performance verified with up to 11 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.