

Manufacturer: GE Lighting
Model Number Tested: LED7DA19V2
Other Model Numbers: PC89884, PC89887, PC94160

Manufacturer's Description

Type of device: LED 7W A-Lamp
 Operating voltage: 120V
 Input Power: 7.0 W
 Input Current: 0.09 A
 Input Frequency: 60Hz

Control Type: Forward and Reverse Phase Control
 Dimming Range: 20-100
 Output Power: Not Specified
 Lumen Output: Not Specified

Lutron Test Results

Date Tested: 10-Sep-13
 Test Voltage: 120 V
 Test Notes: None

Lutron Recommended Compatible Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Fixtures per Dimmer		Measured Dimming Range ⁽¹⁾		Perceived Low End ⁽²⁾	Comments
		Minimum	Maximum	Low End	High End		
<i>Wallbox Dimmers</i>							
Maestro	MACL-153M (L)*	1	21	19%	88%	44%	High end and low end trim required.
Maestro Wireless	MRF2-6ELV	1	21	20%	94%	44%	Low end trim required. Load type not selectable. Evaluated in RP.
Maestro Sensor	MSCL-OP153M (T2)*/ MSCL-VP153M (T2)*	1	21	20%	88%	44%	Low end trim required.
<i>Commercial Systems</i>							
Panel Module	HW/LP-RPM-4A-120	1	128	9%	95%	31%	Low end trim required. Set load type to RP. Rating is per channel; total per module is 204.
Panel Module	HW/LP-RPM-4U-120	1	43	20%	100%	44%	Low end trim required. Rating is per channel; total per module is 43.
Grafik QS	Grafik Eye QS Main Unit Family	1	18	20%	100%	44%	High end and low end trim required. Rating is per output; total quantity per Main Unit is 45.
Panel Module	GP (Harrier) Card	1	43	9%	100%	31%	Low end trim required. Rating is per output.
Grafik Eye 3000	Grafik Eye 3000 Family	1	18	20%	100%	44%	High end and low end trim required. Rating is per output; total quantity per Main Unit is 27, 45, and 45 for 2, 4, and 6 zone units, respectively.
<i>Residential Systems</i>							
RadioRA 2	RRD-10ND	1	21	20%	94%	44%	Low end trim required.
HomeWorks QS	HQRD-10ND	1	21	20%	94%	44%	Low end trim required.
RadioRA 2	RRD-6NA	1	21	20%	94%	44%	Low end trim required. Load type not selectable. Evaluated in RP.
Homeworks QS	HQRD-6NA	1	21	20%	94%	44%	Low end trim required. Load type not selectable. Evaluated in RP.
Panel Module	HW/LP-RPM-4A-120	1	128	9%	95%	31%	Low end trim required. Set load type to RP. Rating is per channel; total per module is 204.

Panel Module	HW/LP-RPM-4U-120	1	43	20%	100%	44%	Low end trim required. Rating is per channel; total per module is 43.
Grafik QS	Grafik Eye QS Main Unit Family	1	18	20%	100%	44%	High end and low end trim required. Rating is per output; total quantity per Main Unit is 45.
Panel Module	GP (Harrier) Card	1	43	9%	100%	31%	Low end trim required. Rating is per output.
Grafik Eye 3000	Grafik Eye 3000 Family	1	18	20%	100%	44%	High end and low end trim required. Rating is per output; total quantity per Main Unit is 27, 45, and 45 for 2, 4, and 6 zone units, respectively.
Interfaces⁽³⁾							
	PHPM-PA with Grafik Eye QS Main Unit	1	205	20%	100%	44%	High end and low end trim required.
	PHPM-WBX with 3-wire fluorescent control	1	205	20%	100%	44%	High end and low end trim required.
Notes:	<p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information</p> <p>(1) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability</p> <p>(2) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook</p> <p>(3) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly</p>						

Test Comments: Performance verified with up to 21 fixtures per control. Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Latest test results can always be found at www.lutron.com/LEDtool.