

[No Product Image available]


LUTRON®
Product Report Card

ID 3068

Manufacturer: GE Lighting Solutions**Model Number Tested:** LRXR618835PH

Other Model Numbers: LRXR618830PH, LRXR618840PH, LRXR818830PH, LRXR818835PH, LRXR818840PH, LRXR618830PHEL, LRXR618840PHEL, LRXR818830PHEL, LRXR818835PHEL, LRXR818840PHEL, LRXS618830PH, LRXS618835PH, LRXS618840PH, LRXS818830PH, LRXS818835PH, LRXS818840PH, LRXS618830PHEL, LRXS618835PHEL, LRXS618840PHEL, LRXS818830PHEL.

Manufacturer's Description

Type of device: LED 19 W Downlight
 Operating voltage: 120V
 Input Power: 19.0 W
 Input Current: 0.16 A
 Input Frequency: 60 Hz

Control Type: Forward and Reverse Phase Control
 Dimming Range: Not Specified
 Output Power: Not Specified
 Lumen Output: 1800 lm
 Type/Shape: Downlight
 Base Type: N/A

Lutron Test ResultsDate Tested: 17-Aug-17Test Voltage: 120 VTest Notes: Performance verified with up to 8 fixtures per control. Test results valid only at 120 V and 60 Hz.**Lutron Recommended Products***Lutron products not in this list can be considered to be not recommended, based on our testing.*

| Product | Model Number | Control Type ⁽¹⁾ | Fixtures per Dimmer ⁽²⁾ | Measured Dimming Range ⁽³⁾ (Software Trim Settings) | | Perceived Low End ⁽⁴⁾ | Comments |
|---|--|-----------------------------|------------------------------------|--|---------|----------------------------------|--|
| | | | | Min-Max | Low End | | |
| Wallbox Dimmers | | | | | | | |
| Diva/ Skylark/ Skylark Contour/ Ariadni/ Toggler/ Lumea | C·L wall-mount dimmers (T8, T9)* | FP | 1 - 7 | 10% | 99% | 31% | |
| Maestro | MACL-153M (TX)* | FP | 1 - 7 | 10% | 99% | 32% | |
| Maestro Wireless | MRF2-6ND | FP | 1 - 7 | 9% | 99% | 31% | |
| Maestro Wireless | MRF2-6ELV | RP | 1 - 7 | 9% | 99% | 29% | Load type not selectable. |
| Maestro Sensor | MSCL-OP153M (T2)*/ MSCL-VP153M (T2)* | FP | 1 - 7 | 9% | 95% | 30% | |
| Caseta Wireless | PD-6WCL (SD11)* | FP | 1 - 7 | 10% | 95% | 31% | |
| Maestro Wireless | MRF2-6CL (M6)* | FP | 1 - 7 | 10% | 96% | 31% | |
| Diva/ Ariadni C250W | 250W C·L dimmers (T5, T8)* | FP | 1 - 13 | 10% | 99% | 31% | |
| Nova T* 250W | NTCL-250 (T8)* | FP | 1 - 13 | 10% | 99% | 31% | |
| Grafik T | GT-150 (T6)* without neutral | FP | 1 - 7 | 11% | 99% | 33% | 2 lamp minimum required without neutral. |
| Grafik T | GTJ-150 (M6)* without neutral | FP | 1 - 7 | 11% | 99% | 33% | 2 lamp minimum required without neutral. |
| Grafik T | GTJ-250M (M6)*/GT-250M (T7)* without neutral | FP | 1 - 13 | 11% | 99% | 33% | 2 lamp minimum required without neutral. |
| Caseta Wireless | PD-10NXD (SD11)* without neutral | FP | 1 - 13 | 10% | 95% | 31% | |

| | | | | | | | |
|------------------------------------|--|----|--------|----------|----------|-----|---|
| Skylark Contour Slide to-off | CTCL-150 | FP | 1 - 7 | 10% | 99% | 31% | |
| Caseta Wireless Phase Selectable | PD-5NE | RP | 1 - 13 | 7% | 99% | 25% | |
| Commercial Systems | | | | | | | |
| Stanza | SZ-6ND | FP | 1 - 8 | 10% (18) | 99% (99) | 31% | |
| Panel Module | HW/LP-RPM-4A-120 | RP | 1 - 63 | 10% (34) | 99% (99) | 32% | Rating is per channel; total per module is 100. |
| Panel Module | HW/LP-RPM-4U-120 | FP | 1 - 37 | 9% (25) | 99% (99) | 30% | Rating is per channel; total per module is 37. |
| Grafik QS/ Wallbox Power Module | Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P | FP | 1 - 37 | 10% (25) | 99% (82) | 31% | Rating is per output; total quantity per Main Unit is 92. |
| Panel Module | GP (Harrier) Card | FP | 1 - 37 | 12% (23) | 99% (99) | 35% | Rating is per output. Use load type 2-1. |
| Grafik Eye 3000/ HomeWorks | Grafik Eye 3000 Family/ HWI-WPM-6D-120 | FP | 1 - 37 | 10% (25) | 99% (82) | 31% | Rating is per output; total quantity per Main Unit is 55/69/92/92 for 2/3/4/6-Zone units, respectively. |
| HomeWorksQS/ myRoom | LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP | RP | 1 - 6 | 10% (33) | 99% (99) | 32% | Rating is per output; total quantity per Main Unit is 24. |
| Vive | MRF2S-6ND | FP | 1 - 7 | 9% | 99% | 31% | |
| Vive | MRF2S-6ELV | RP | 1 - 7 | 9% (41) | 99% (99) | 29% | |
| Vive | MRF2S-6CL | FP | 1 - 7 | 10% (34) | 96% (99) | 31% | |
| Residential Systems | | | | | | | |
| RadioRA 2 | RRD-10ND | FP | 1 - 7 | 9% (27) | 99% (99) | 31% | |
| HomeWorks QS | HQRD-6ND | FP | 1 - 7 | 9% (27) | 99% (99) | 31% | |
| HomeWorks QS | HQRD-10ND | FP | 1 - 7 | 9% (27) | 99% (99) | 31% | |
| RadioRA 2 | RRD-6NA | RP | 1 - 7 | 9% (41) | 99% (99) | 29% | |
| HomeWorks QS | HQRD-6NA | RP | 1 - 7 | 9% (41) | 99% (99) | 29% | |
| HomeWorks | HxD-6ND | FP | 1 - 8 | 10% (18) | 99% (99) | 31% | |
| Panel Module | HW/LP-RPM-4A-120 | RP | 1 - 63 | 10% (34) | 99% (99) | 32% | Rating is per channel; total per module is 100. |
| Panel Module | HW/LP-RPM-4U-120 | FP | 1 - 37 | 9% (25) | 99% (99) | 30% | Rating is per channel; total per module is 37. |
| Grafik QS/ Wallbox Power Module | Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P | FP | 1 - 37 | 10% (25) | 99% (82) | 31% | Rating is per output; total quantity per Main Unit is 92. |
| Panel Module | GP (Harrier) Card | FP | 1 - 37 | 12% (23) | 99% (99) | 35% | Rating is per output. Use load type 2-1. |
| Grafik Eye 3000/ HomeWorks | Grafik Eye 3000 Family/ HWI-WPM-6D-120 | FP | 1 - 37 | 10% (25) | 99% (82) | 31% | Rating is per output; total quantity per Main Unit is 55/69/92/92 for 2/3/4/6-Zone units, respectively. |
| RadioRA 2 | RRD-6CL (R3)* | FP | 1 - 7 | 10% (34) | 96% (99) | 31% | |
| HomeWorks QS | HQRD-6CL (H2)*/ HQRA-6CL (H2)* | FP | 1 - 7 | 10% (34) | 96% (99) | 31% | |
| RadioRA 2 | RRD-6D | FP | 1 - 7 | 9% (27) | 99% (99) | 30% | |
| RadioRA 2 | Hybrid Keypad C.L RRD- HN6BRL | FP | 1 - 5 | 9% (28) | 99% (99) | 29% | Installation with a neutral wire is required. |
| HomeWorks QS | Hybrid Keypad C.L HQRD- HN6BRL | FP | 1 - 5 | 9% (28) | 99% (99) | 29% | Installation with a neutral wire is required. |
| RadioRA 2 | RRT-G25LW (R3)* without neutral | FP | 1 - 13 | 11% | 99% | 33% | 2 lamp minimum required without neutral. |
| HomeWorks QS | HQRT-G25LW (H2)* without neutral | FP | 1 - 13 | 11% | 99% | 33% | 2 lamp minimum required without neutral. |

| | | | | | | | |
|----------------------------------|--|----|---------|----------|----------|-----|--|
| HomeWorksQS/ myRoom | LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 120V, RP | RP | 1 - 6 | 10% (33) | 99% (99) | 32% | Rating is per output; total quantity per Main Unit is 24. |
| Interfaces ⁽⁵⁾ | | | | | | | |
| | PHPM-PA with Grafik Eye QS Main Unit | RP | 1 - 101 | 10% (37) | 99% (84) | 31% | |
| | PHPM-WBX with 3-wire fluorescent control | RP | 1 - 101 | 10% | 99% | 31% | |
| Notes: | <p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p> | | | | | | |

Test Comments: Performance verified with up to 8 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.