



ID: 3849

## Product Report Card

**Manufacturer:** Girard Sudron

**Model Number Tested:** 716673

Other Model Numbers:

### Manufacturer's Description

Type of Device: LED 4 W A21

Operating Voltage: 240

Input Power: 4 W

Input Current: 0.019 A

Input Frequency: 50 Hz

Control Type: Forward and Reverse Phase Control

Dimming Range: Not Specified

Output Power: Not Specified

Lumen Output: 160 lm

Type/Shape: A21

Base Type: E27

### Lutron Test Results

Date Tested 12/17/2018

Test Voltage 240 V

Test Notes Test results valid only at 240V and 50 Hz.

### Lutron Recommended Products

*Lutron products not in this list can be considered to be not recommended, based on our testing.*

Product	Model Number	Control Type <sup>(1)</sup>	Fixtures per Dimmer <sup>(2)</sup>	Measured Dimming Range <sup>(3)</sup> (Software Trim Settings)		Perceived Low End <sup>(4)</sup>	Comments
			Min-Max	Low End	High End		
<i>Commercial Systems</i>							
Panel Module	GP (Harrier) Card	FP	1 - 114	10%	98%	32%	Rating is per output. Use load type 2-1.
HomeWorks QS/ESN Phase Adaptive	LQSE-4A-D (Gen. 2)/QSNE-4A-D (Gen. 2)	RP	1 - 16	10%	99%	32%	Rating is per zone. Performance may vary with dimmers manufactured before March 2014.
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP	RP	1 - 7	10%	99%	31%	
Grafik Integrale	GXI-3104	RP	1 - 27	10%	100%	31%	Need per output and total per module comment. Rating is per channel; total per module is 40.
<i>Interfaces</i>							
Load Interfaces	NGRX-ELVI-CE with Grafik Eye QS Main Unit, 240V	RP	1 - 39	10%	99%	32%	

Product	Model Number	Control Type <sup>(1)</sup>	Fixtures per Dimmer <sup>(2)</sup>	Measured Dimming Range <sup>(3)</sup> (Software Trim Settings)		Perceived Low End <sup>(4)</sup>	Comments
			Min-Max	Low End	High End		
Load Interfaces	NGRX-PB-CE with Grafik Eye QS Main Unit, 240V	FP	1 - 39	9%	98%	31%	

### Residential Systems

Panel Module	GP (Harrier) Card	FP	1 - 114	10%	98%	32%	Rating is per output. Use load type 2-1.
HomeWorks QS/ESN Phase Adaptive	LQSE-4A-D (Gen. 2)/QSNE-4A-D (Gen. 2)	RP	1 - 16	10%	99%	32%	Rating is per zone. Performance may vary with dimmers manufactured before March 2014.
HomeWorksQS/myRoom	LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP	RP	1 - 7	10%	99%	31%	
RA2 Select	RRK-R25NE-240	RP	1 - 7	10%	100%	32%	
Homeworks QS	HQRK-R25NE-240	RP	1 - 7	10%	100%	32%	
Homeworks QS	HQRM-R25NE-240	RP	1 - 7	10%	100%	32%	

### WallBox Dimmers

No applicable results

Notes:

- \* Identical model numbers with different compatibility codes may have different performance; ( ) means there is no compatibility code assigned; contact technical support for additional information.
- (1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.
- (2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.
- (3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.
- (4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.
- (5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.

This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at [www.lutron.com/LEDtool](http://www.lutron.com/LEDtool).