

REPORT CARD

(For fixtures using the Lutron
Hi-lume® A-Series LED Driver)



***REQUIRED FIELDS**

Manufacturer:*	Various Brands
Website:*	See list of all High Performance LED Fixtures at http://www.lutron.com/findafixture
Applicable model numbers:*	See manufacturer-specific spec sheets for details
Date:*	

Fixture manufacturer's description			
Type of fixture:*	Choose from list at right ►	<input checked="" type="checkbox"/> Cove/Strip light	<input checked="" type="checkbox"/> Pucklight
Operating voltage:	120V	<input checked="" type="checkbox"/> Downlight	<input checked="" type="checkbox"/> Sconce
Control type:	2-wire forward phase (with neutral)	<input checked="" type="checkbox"/> Linear LEDs	<input checked="" type="checkbox"/> Troffer fixture
Dimming range:	100% – 1%	<input checked="" type="checkbox"/> Light engine	<input checked="" type="checkbox"/> Wallwash
Input power (max.):*	Varies	<input checked="" type="checkbox"/> Pendant	

Driver manufacturer: Lutron Electronics
Product: Hi-lume A-Series LED driver



Compatible Lutron products

Product family	Part number	Fixtures per dimmer (120V only)*	Measured light output range
NovaT☆®	NTLV-600-CPN0199	1 – 8	100% – 1%
Maestro Wireless®	MRF2-6ND-120	1 – 8	100% – 1%
RadioRA® 2 1000W	RRD-10ND	1 – 13	100% – 1%
RadioRA 2 adaptive dimmer	RRD-6NA	1 – 8	100% – 1%
RadioRA 600W	RA-6ND	1 – 8	100% – 1%
RadioRA 1000W	RA-10ND	1 – 13	100% – 1%
HomeWorks® QS 600W (LED*)	HQRD-6ND	1 – 8	100% – 1%
HomeWorks QS 1000W (LED*)	HQRD-10ND	1 – 13	100% – 1%
HomeWorks QS adaptive dimmer	HQRD-6NA	1 – 8	100% – 1%
HomeWorks QS WPM (LED*)	HQRJ-WPM-6D-120	1 – 10 (per output)	100% – 1%
HomeWorks 600W dimmer	HRD-6ND	1 – 8	100% – 1%
HomeWorks 1000W dimmer	HWD-10ND, HRD-10ND	1 – 13	100% – 1%
HomeWorks WPM	HWI-WPM-6D-120	1 – 10 (per output)	100% – 1%
GRAFIK Eye® QS (fluorescent*)	QSGR-, QSGRJ-	1 – 10 (per output)	100% – 1%
GRAFIK Eye 3000(fluorescent*)	GRX-3100, GRX-3500	1 – 10 (per output)	100% – 1%
RPM-4U module, (LCP, HomeWorks, GRAFIK Systems, Quantum®)	HW-RPM-4U-120, LP-RPM-4U-120	1 – 26 (per output)	100% – 1%
RPM-4A module (LCP, HomeWorks, GRAFIK Systems, Quantum) (LED*)	HW-RPM-4A-120, LP-RPM-4A-120	1 – 13 (per output)	100% – 1%
GP panels (LCP, HomeWorks, GRAFIK Systems, Quantum)	Various	1 – 26	100% – 1%
Stanza®	SZ-6ND	1 – 8	100% – 1%

* Set load type before adjusting low-end trim.

NOTE: Contact Lutron tech support for degangng rules when using wallbox controls on the Hi-lume A-Series LED Driver.

NOTE: Low-end trim may need to be adjusted to achieve 1% dimming.

For information on low-end trim adjustment, consult installation instructions.