



# LUTRON® Product Report Card

ID 885

**Manufacturer:** Philips Lightolier  
**Model Number Tested:** 1076WHL30K  
**Other Model Numbers:** 1076L Series and 1013 Series

**Manufacturer's Description**

Type of device:	<u>LED Recessed LED Downlight-Lytecaster</u>	Control Type:	<u>Forward and Reverse Phase Control</u>
Operating voltage:	<u>120V</u>	Dimming Range:	<u>Not Specified</u>
Input Power:	<u>13.0W</u>	Output Power:	<u>Not Specified</u>
Input Current:	<u>Not Specified</u>	Lumen Output:	<u>Not Specified</u>
Input Frequency:	<u>60Hz</u>		

**Lutron Test Results**

Date Tested: 23-Jan-13  
 Test Voltage: 120 V  
 Test Notes: None

**Lutron Recommended Compatible Products**

*Lutron products not in this list can be considered to be not recommended, based on our testing.*

Product	Model Number	Fixtures per Dimmer		Measured Dimming Range <sup>(1)</sup>		Perceived Low End <sup>(2)</sup>	Comments
		Minimum	Maximum	Low End	High End		
<i>Wallbox Dimmers</i>							
Maestro RF	MRF2-6ELV	1	11	20%	100%	44%	Buzzing may be noticed. Set load type to RP.
<i>Commercial Systems</i>							
Stanza	SZ-6ND	1	8	5%	100%	23%	
Panel Module	HW/LP-RPM-4A-120	1	64	5%	100%	21%	Set load type to RP. Rating is per channel; total per module is 102.
Panel Module	HW/LP-RPM-4U-120	1	28	2%	100%	15%	Rating is per channel; total per module is 28.
Grafik QS	Grafik Eye QS Main Unit Family	1	11	6%	100%	24%	Rating is per output; total per Main Unit is 27.
Panel Module	GP (Harrier) Card	1	28	4%	100%	19%	Rating is per output.
<i>Residential Systems</i>							
RadioRA 2	RRD-10ND	1	11	20%	100%	44%	Buzzing may be noticed.
HomeWorks QS	HQRD-10ND	1	11	20%	100%	44%	Buzzing may be noticed.
RadioRA 2	RRD-6NA	1	11	20%	100%	44%	Buzzing may be noticed. Set load type to RP.
Homeworks QS	HQRD-6NA	1	11	20%	100%	44%	Buzzing may be noticed. Set load type to RP.
HomeWorks	HxD-6ND	1	8	5%	100%	23%	
Panel Module	HW/LP-RPM-4A-120	1	64	5%	100%	21%	Set load type to RP. Rating is per channel; total per module is 102.
Panel Module	HW/LP-RPM-4U-120	1	28	2%	100%	15%	Rating is per channel; total per module is 28.
Grafik QS	Grafik Eye QS Main Unit Family	1	11	6%	100%	24%	Rating is per output; total per Main Unit is 27.
Panel Module	GP (Harrier) Card	1	28	4%	100%	19%	Rating is per output.
<i>Interfaces <sup>(3)</sup></i>							
	PHPM-PA with Grafik Eye QS Main Unit	1	102	4%	99%	20%	
	PHPM-WBX with 3-wire fluorescent control	1	102	4%	99%	20%	

Notes:	(1) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability (2) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook (3) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly
--------	---

Test Comments: Performance verified with up to 11 fixtures per control. Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.

*For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Latest test results can always be found at [www.lutron.com/LEDtool](http://www.lutron.com/LEDtool).*