



LUTRON® Product Report Card

ID 2752

Manufacturer: Osram
Model Number Tested: AB43370
Other Model Numbers: None

Manufacturer's Description

Type of device: LED 10 W A19
 Operating voltage: 240V
 Input Power: 10.0 W
 Input Current: 0.05 A
 Input Frequency: 50 Hz

Control Type: Forward and Reverse Phase Control
 Dimming Range: Not Specified
 Output Power: Not Specified
 Lumen Output: 806 lm
 Type/Shape: A19
 Base Type: E27

Lutron Test Results

Date Tested: 7-Feb-17
 Test Voltage: 240 V
 Test Notes: Performance verified with up to 10 fixtures per control. Test results valid only at 240 V and 50 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

| Product | Model Number | Control Type ⁽¹⁾ | Fixtures per Dimmer ⁽²⁾ | Measured Dimming Range ⁽³⁾ (Software Trim Settings) | | Perceived Low End ⁽⁴⁾ | Comments |
|-------------------------------------|---|-----------------------------|------------------------------------|--|----------|----------------------------------|---|
| | | | Min-Max | Low End | High End | | |
| <i>Wallbox Dimmers</i> | | | | | | | |
| <i>No applicable results</i> | | | | | | | |
| <i>Commercial Systems</i> | | | | | | | |
| Panel Module | HW/LP-RPM-4A-230 | RP | 1 - 7 | 2% (1) | 97% (80) | 14% | Rating is per channel; total per module is 7. Rating is per channel; total per module is 7. |
| Panel Module | HW/LP-RPM-4U-230-CE | FP | 1 - 8 | 1% (1) | 98% (80) | 12% | Rating is per channel; total per module is 10. |
| Panel Module | GP (Harrier) Card | FP | 1 - 13 | 2% (1) | 95% (99) | 15% | Rating is per output. Use load type 2-1. |
| Grafik QS/ Wallbox Power Module | Grafik Eye QS Main Unit Family, 240V/ LQR-WPM-6PCE | FP | 1 - 4 | 2% (5) | 95% (99) | 15% | Rating is per output; total quantity per Main Unit is 12/16/18 for 3/4/6-Zone units, respectively. |
| Grafik Eye/ HomeWorks | GRX-3104-CE/ HWI-WPM-6D-230CE | FP | 1 - 2 | 2% | 95% | 13% | Rating is per output; total quantity per Main Unit is 4/5/5/5 for 2/3/4/6-Zone units, respectively. |
| HomeWorks QS/ ESN Phase Adaptive | LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)* | FP | 1 - 1 | 3% (11) | 97% (98) | 17% | Rating is per zone. Performance may vary with dimmers manufactured before March 2014. |
| HomeWorks QS/ ESN Phase Adaptive | LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)* | RP | 1 - 1 | 5% (12) | 98% (98) | 22% | Rating is per zone. Performance may vary with dimmers manufactured before March 2014. |
| HomeWorksQS/ myRoom | LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 240V, RP | RP | 1 - 9 | 2% (1) | 96% (99) | 14% | Rating is per output; total quantity per Main Unit is 36. |

| | | | | | | | |
|-------------------------------------|--|----|--------|---------|----------|-----|---|
| Grafik Integrale | GXI-3104 | RP | 1 - 3 | 1% | 98% | 12% | Need per output and total per module comment. Rating is per channel; total per module is 7. |
| Residential Systems | | | | | | | |
| Panel Module | HW/LP-RPM-4A-230 | RP | 1 - 7 | 2% (1) | 97% (80) | 14% | Rating is per channel; total per module is 7. Rating is per channel; total per module is 7. |
| Panel Module | HW/LP-RPM-4U-230-CE | FP | 1 - 8 | 1% (1) | 98% (80) | 12% | Rating is per channel; total per module is 10. |
| Panel Module | GP (Harrier) Card | FP | 1 - 13 | 2% (1) | 95% (99) | 15% | Rating is per output. Use load type 2-1. |
| Grafik QS/ Wallbox Power Module | Grafik Eye QS Main Unit Family, 240V/ LQR-WPM-6PCE | FP | 1 - 4 | 2% (5) | 95% (99) | 15% | Rating is per output; total quantity per Main Unit is 12/16/18 for 3/4/6-Zone units, respectively. |
| Grafik Eye/ HomeWorks | GRX-3104-CE/ HWI-WPM-6D-230CE | FP | 1 - 2 | 2% | 95% | 13% | Rating is per output; total quantity per Main Unit is 4/5/5/5 for 2/3/4/6-Zone units, respectively. |
| HomeWorks QS/ ESN Phase Adaptive | LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)* | FP | 1 - 1 | 3% (11) | 97% (98) | 17% | Rating is per zone. Performance may vary with dimmers manufactured before March 2014. |
| HomeWorks QS/ ESN Phase Adaptive | LQSE-4A-D (Gen. 2)*/ QSNE-4A-D (Gen. 2)* | RP | 1 - 1 | 5% (12) | 98% (98) | 22% | Rating is per zone. Performance may vary with dimmers manufactured before March 2014. |
| HomeWorksQS/ myRoom | LQSE-4A1-D/ MQSE-4A1-D/ MQSE-3A1/ MQSE-2A1-D, 240V, RP | RP | 1 - 9 | 2% (1) | 96% (99) | 14% | Rating is per output; total quantity per Main Unit is 36. |
| Interfaces ⁽⁵⁾ | | | | | | | |
| | NGRX-ELVI-CE with Grafik Eye QS Main Unit, 240V | RP | 1 - 4 | 3% (27) | 96% (80) | 17% | |
| | NGRX-PB-CE with Grafik Eye QS Main Unit, 240V | FP | 1 - 4 | 2% (5) | 96% (85) | 14% | |
| Notes: | <p>* Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information.</p> <p>(1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details.</p> <p>(2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control.</p> <p>(3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable.</p> <p>(4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook.</p> <p>(5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.</p> | | | | | | |

Test Comments: Performance verified with up to 10 fixtures per control.

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com. This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.