

Product Report Card

Manufacturer: **Vitality**
Model Number Tested: **YM0040CPFPD3**
Other Model Numbers: **YM3640RIFPD3**

Manufacturer's Description

Type of Device: LED 60 W Mirror Light
 Operating Voltage: 120
 Input Power: 60 W
 Input Current: 0.65 A
 Input Frequency: 60 Hz

Control Type: Forward Phase
 Dimming Range: Not Specified
 Output Power: Not Specified
 Lumen Output: Not Specified
 Type/Shape: Mirror Light
 Base Type: N/A

Lutron Test Results

Date Tested 06/01/2018
 Test Voltage 120 V
 Test Notes Test results valid only at 120V and 60 Hz.

Lutron Recommended Products

Lutron products not in this list can be considered to be not recommended, based on our testing.

Product	Model Number	Control Type ⁽¹⁾	Fixtures per Dimmer ⁽²⁾	Measured Dimming Range ⁽³⁾ (Software Trim Settings)		Perceived Low End ⁽⁴⁾	Comments
				Min-Max	Low End		
Commercial Systems							
Stanza	SZ-6ND	FP	1 - 1	6%	98%	24%	
Panel Module	HW/LP-RPM-4A-120	FP	1 - 1	6%	97%	24%	
Panel Module	HW/LP-RPM-4U-120	FP	1 - 9	5%	97%	22%	
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 7	5%	96%	22%	
Panel Module	GP (Harrier) Card	FP	1 - 9	6%	98%	24%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 7	5%	96%	22%	
Vive	MRF2S-6CL	FP	1 - 2	18%	94%	42%	

Interfaces

No applicable results

Residential Systems

HomeWorks	HxD-6ND	FP	1 - 1	6%	98%	24%	
Panel Module	HW/LP-RPM-4A-120	FP	1 - 1	6%	97%	24%	
Panel Module	HW/LP-RPM-4U-120	FP	1 - 9	5%	97%	22%	

Product	Model Number	Control Type	Fixtures per Dimmer	Measured Dimming Range (Software Trim Settings)		Perceived Low End	Comments
			Min-Max	Low End	High End		
Grafik QS/Wallbox Power Module	Grafik Eye QS Main Unit Family/LQRJ-WPM-6P	FP	1 - 7	5%	96%	22%	
Panel Module	GP (Harrier) Card	FP	1 - 9	6%	98%	24%	Rating is per output. Use load type 2-1.
Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	FP	1 - 7	5%	96%	22%	
RadioRA 2	RRD-6CL (R3)	FP	1 - 2	18%	94%	42%	
HomeWorks QS	HQRD-6CL (H2)/HQRA-6CL (H2)	FP	1 - 2	18%	94%	42%	
RadioRA 2	Hybrid Keypad C.L RRD-HN6BRL	FP	1 - 1	8%	96%	28%	Installation with a neutral wire is required.
HomeWorks QS	Hybrid Keypad C.L HQRD-HN6BRL	FP	1 - 1	8%	96%	28%	Installation with a neutral wire is required.
RadioRA 2	RRT-G25LW (R3) without neutral	FP	1 - 4	8%	98%	28%	2 lamp minimum required without neutral.
HomeWorks QS	HQRT-G25LW (H2) without neutral	FP	1 - 4	8%	98%	28%	2 lamp minimum required without neutral.
Homeworks QS	LQSE-4A-120-D, FP	FP	1 - 0	6%	98%	24%	

WallBox Dimmers

Diva/Skylark/Skylark Contour/Ariadni/Toggler/ Lumea	CL wall-mount dimmers (T8, T9)	FP	1 - 2	6%	98%	24%	
Maestro	MACL-153M (TX)	FP	1 - 2	5%	99%	22%	
Maestro Sensor	MSCL-OP153M (T2)/MSCL-VP153M (T2)	FP	1 - 2	7%	98%	26%	
Caseta Wireless	PD-6WCL (SD11)	FP	1 - 2	6%	98%	24%	
Maestro Wireless	MRF2-6CL (M6)	FP	1 - 2	18%	94%	42%	
Diva/Ariadni C250W	250W CL dimmers (T5,T8)	FP	1 - 4	6%	98%	24%	
Nova T* 250W	NTCL-250 (T8)	FP	1 - 4	6%	98%	24%	
Grafik T	GT-150 (T6) without neutral	FP	1 - 2	8%	98%	28%	2 lamp minimum required without neutral.
Grafik T	GTJ-150 (M6) without neutral	FP	1 - 2	8%	98%	28%	2 lamp minimum required without neutral.
Grafik T	GTJ-250M (M6)/GT-250M (T7) without neutral	FP	1 - 4	8%	98%	28%	2 lamp minimum required without neutral.
Caseta Wireless	PD-10NXD (SD11) without neutral	FP	1 - 4	6%	98%	24%	
Skylark Contour Slide to-off	CTCL-150	FP	1 - 2	6%	98%	24%	
Maestro	MACL-LFQ	FP	1 - 1	5%	98%	22%	

Notes:	<ul style="list-style-type: none"> * Identical model numbers with different compatibility codes may have different performance; () means there is no compatibility code assigned; contact technical support for additional information. (1) Control types of FP and RP represent Forward Phase and Reverse Phase, respectively. See product literature for details. (2) Maximum Fixtures per Dimmer value represents the maximum safe loading of the control. (3) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability. Values are set to optimize performance, such as reducing dead travel, ensuring that fixtures turn on at low end, reducing turn-on time at low end, and trimming out instability. Software trim values are indicated in parentheses when applicable. (4) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook. (5) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly.
--------	---

For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.

This information was posted with the consent and cooperation of the device manufacturer. Please be aware that device manufacturers may modify their product at any time, without notice to Lutron, and therefore Lutron cannot ensure future compatibility. For more detailed and up to date fixture specifications, performance and/or any related recall information, visit the manufacturer's website. The latest Lutron test results can always be found at www.lutron.com/LEDtool.
