



LUTRON®

Product Report Card

Manufacturer: General Electric
 Model Number Tested: LED7DP20S830/20
 Other Model Numbers: None

Manufacturer's Description

Type of device: <u>7watt PAR20</u> Operating voltage: <u>120V</u> Input Power: <u>7 W</u> Input Current: <u>Not Specified</u> Input Frequency: <u>Not Specified</u>	Control Type: <u>Unspecified Phase Control</u> Dimming Range: <u>Not Specified</u> Output Power: <u>Not Specified</u> Lumen Output: <u>330</u>
---	---

Lutron Test Results

Date Tested: 6-May-11
 Figure of Merit: N/A
 Test Voltage: 120 V
 Test Notes: None

Lutron Recommended Compatible Products

Lutron products not in this list can be considered to be not compatible, based on our testing.

Product	Model Number	Fixtures per Dimmer		Measured Dimming Range ⁽¹⁾		Perceived Low End ⁽²⁾	Comments
		Minimum	Maximum	Low End	High End		
<i>Wallbox Dimmers</i>							
All C.L Dimmers	DV(W)CL-153P CTCL-153P	1	21	15%	83%	39%	Start time about 1.5 seconds.
<i>Commercial Systems</i>							
Panel Module	HW/LP-RPM-4A-120	1	137	16%	94%	40%	
Grafik QS	Grafik Eye QS Main Unit Family	1	19	14%	98%	38%	Start time about 1.5 seconds. Minor shimmer at LE.
Panel Module	GP (Harrier) Card	1	47	16%	98%	39%	
<i>Residential Systems</i>							
Panel Module	HW/LP-RPM-4A-120	1	137	16%	94%	40%	
HomeWorks	HxD-6ND	1	14	14%	93%	38%	Start time about 1.5 seconds
Grafik QS	Grafik Eye QS Main Unit Family	1	19	14%	98%	38%	Start time about 1.5 seconds. Minor shimmer at LE.
Panel Module	GP (Harrier) Card	1	47	16%	98%	39%	
RadioRA 2	RRD-10ND	1	23	15%	95%	39%	Start time about 2 seconds
RadioRA 2	RRD-6NA	1	68	15%	89%	39%	Start time about 1.5 seconds
<i>Interfaces ⁽³⁾</i>							
	PHPM-WBX with DVF-103P	1	229	15%	99%	38%	Start time about 1.5 seconds
	PHPM-PA with QSG-6D	1	229	15%	100%	38%	Start time about 1.5 seconds
Notes:	(1) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability (2) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook (3) Interfaces have been tested with the listed control; any compatible dimmer may be used instead, but high end/low end light levels may vary slightly						

Test Comments: None

*For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com
 This information was posted with the consent and cooperation of the device manufacturer. Latest test results can always be found at www.lutron.com/LEDtool.*