



LED Product Report Card

Manufacturer: Juno
 Applicable Model Numbers: IC20LED-3K, IC20LED-35K, IC20LED-41K, IC22LED-3K, IC22LED-35K, IC22LED-41K

Manufacturer's Description

Type of Fixture: Recessed Downlight
 Operating Voltage: 120 / 277 Vac
 Input Power: 14.2 W
 Current: 0.128 A
 Frequency: 60 Hz
 Control Types: Electronic Low Voltage (reverse phase)
 Dimming Range: Not Specified
 Output Power: N/A
 Lumens: 684 lm (with clear lens)

Lutron Test Results

Date Tested: October 10, 2009
 Model Number Tested: IC22LED-35K (Driver Rev. F)
 Smooth and Continuous: Yes
 Test Notes:

Lutron Recommended Compatible Products

Product	Part Number	Fixtures per Dimmer	Measured Light Output Range ⁽¹⁾	Comments
Homeworks	HW-RPM-4A-120	1 – 85 per output	10% - 80%	Max. 135 fixtures per module Low-end trim available
Commercial Systems	LP-RPM-4A-120	1 – 85 per output	10% - 80%	Max. 135 fixtures per module Low-end trim available
Interfaces	PHPM-WBX ⁽²⁾	4 – 140	7% - 80%	Low-end trim available
	PHPM-PA ⁽³⁾	4 – 140	7% - 80%	Low-end trim available

⁽¹⁾ Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full capability

⁽²⁾ Controlled with Ariadni, Diva, Lyneo Lx, Maestro, Nova, Nova T*, Skylark, or Vareo 3-wire Fluorescent dimmers, or a GrafikEye

⁽³⁾ Controlled with HomeWorks or Commercial Systems.

Comments: These recommendations are for 120Vac / 60 Hz operation only.

The ability to set the low-end trim is available on select 3-Wire Fluorescent dimmers, Homeworks, and Commercial Systems products. Refer to product documentation or www.lutron.com for details. For best low-end performance, the low-end output should be set above 27 Volts AC. The fixtures will work below this level, but may lead to longer low-end start delays.