


LUTRON®
Product Report Card

Manufacturer: KolourOne by Satco
 Model Number Tested: P38-017UD-W****-E26
 Other Model Numbers: 0

Manufacturer's Description

Type of device: LED Control Type: Unspecified Phase Control
 Operating voltage: 120V Dimming Range: Not Specified
 Input Power: Not Specified Output Power: Not Specified
 Input Current: 120 Lumen Output: Not Specified
 Input Frequency: 60Hz

Lutron Test Results

Date Tested: 8-Jul-10
 Figure of Merit: N/A
 Test Notes: None

Lutron Recommended Compatible Products

Lutron products not in this list can be considered to be not compatible, based on our testing.

| Product | Model Number | Fixtures per Dimmer | | Measured Dimming Range ⁽¹⁾ | | Perceived Low End ⁽²⁾ | Comments |
|------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------|---------|---------------------------------------|----------|----------------------------------|------------------------------------------------------------|
| | | Minimum | Maximum | Low End | High End | | |
| <i>Wallbox Dimmers</i> | | | | | | | |
| <i>No applicable results</i> | | | | | | | |
| <i>Commercial Systems</i> | | | | | | | |
| Panel Module | HW/LP-RPM-4A-120 | 1 | 17 | 18% | 98% | 42% | Low end trim required. 12 fixtures per output. |
| Panel Module | HW/LP-RPM-4U-120 | 1 | 17 | 5% | 95% | 23% | Low end trim required. 12 fixtures per output. |
| Grafik QS | QSG-6D | 1 | 7 | 3% | 91% | 16% | Low end trim required. Maximum of 17 fixtures per control. |
| Stanza | SZ-6ND | 1 | 5 | 4% | 84% | 19% | Low end trim required. |
| <i>Residential Systems</i> | | | | | | | |
| Panel Module | HW/LP-RPM-4A-120 | 1 | 17 | 18% | 98% | 42% | Low end trim required. 12 fixtures per output. |
| Panel Module | HW/LP-RPM-4U-120 | 1 | 17 | 5% | 95% | 23% | Low end trim required. 12 fixtures per output. |
| Grafik QS | QSG-6D | 1 | 7 | 3% | 91% | 16% | Low end trim required. Maximum of 17 fixtures per control. |
| Radio RA 2 | RRD-6NA | 1 | 5 | 7% | 100% | 27% | |
| <i>Interfaces</i> | | | | | | | |
| | PHPM-WBX with DV-103P | 1 | 18 | 7% | 94% | 26% | Startup delay about 2 sec. |
| | PHPM-PA with QSG-6D | 1 | 18 | 3% | 102% | 17% | |
| Notes: | (1) Values are based on light output using the specified dimming control, and may not be an indication of the fixture's full rated capability (2) Perceived light level percentage is the square root of the measured light level percentage, per IESNA Lighting Handbook | | | | | | |

Test Comments: None

*For any questions on this report, please contact the Lutron LED Center of Excellence at 877-DIM-LED8 or leds@lutron.com.
 This information was posted with the consent and cooperation of the device manufacturer.*